

- 1 -

A METHOD OF INSPECTING A DNA CHIP AND
AN APPARATUS THEREOF

BACKGROUND OF THE INVENTION

095933-10400
The present invention relates to an apparatus
for reading and analyzing an emitted light (fluorescent
light) pattern emitted from a sample located on a
5 plane. More particularly, it relates to a method and
an apparatus by which living body samples, such as a
DNA, a RNA and an oligonucleotide marked by a fluo-
rescent material, are trapped at a plurality of
positions on a substrate so as to read an emitted light
10 pattern from the fluorescent marker with a high-
resolution, at a high-speed and with a high-
sensitivity.

Analysis technologies for analyzing the DNA
and proteins are important in fields of medicine and
15 biology including gene analysis and gene diagnosis. In
particular, in recent years, attention has been focused
on a method and an apparatus by which, using a DNA
probe array (which is called in other way by various
names such as oligochip, DNA chip or biochip, but here-
20 inafter the DNA probe array is employed as the generic
name), a variety types of DNA sequence information and
gene information are inspected and analyzed simultane-
ously from one specimen to be inspected. The DNA probe
array is implemented in the following way: A substrate

such as a glass is used and separated into a plurality of (millions to tens of millions) areas, and target (usually, different types of) DNA probes are fixed onto the respective areas so as to form the respective areas into microscopic reaction areas, thus implementing the array. The reaction of the specimen with the array allows a target DNA in the specimen to be trapped in a state of being hybridized with the fixed DNA probes. Moreover, the target DNA is coupled with a probe such as a fluorescent probe, thereby making it possible to measure the coupled state (the position, i.e., the hybridized sequence) and its quantity with the use of the fluorescence intensity and so on. This permits the array to be utilized in the gene diagnosis and the sequence.

A microscope-like apparatus (confocal fluorescent microscope), which is usually called a scanner, is used in order to read the fluorescence intensity emitted from the fluorescent marker on the target DNA trapped in the respective reaction areas of the DNA probe array (for example, refer to JP-A-11-315095). In this apparatus, the array is irradiated with a excitation light such as a laser light which has been modified into one microscopic spot-shaped configuration, and fluorescent lights generated are separated from the excitation light using a spectroscopic device such as an interference filter, then detecting the fluorescence intensity using a photo detector such as a

photomultiplier tube. At that time, the excitation light is waved using a galvanometer mirror so as to scan, in a 2-dimensional manner, the microscopic spot formed on the array. Otherwise, the position of the
5 microscopic spot is fixed, then scanning the array in the 2-dimensional manner. These scans make it possible to recognize the fluorescence intensity distribution of the entire array, i.e., the degree of the coupling toward each DNA probe.

10 When trying to apply the DNA inspection to a living body inspection such as a conventional blood inspection, it becomes absolutely required to execute the inspection toward a large number of living
15 specimens at a high-speed. In the conventional technologies, however, it takes so much inspection time to irradiate one point with the excitation light spot, which is equivalent to a necessary inspecting resolution of the DNA chip, and to detect the obtained
20 fluorescent lights one after another. This is concerned with the fact that it is impossible to shorten unlimitedly a time needed to detect this one point. Namely, this is attributed to the fact that the time Δt_L , which is needed up to the finishing of the
25 fluorescent light generation after the irradiation with the excitation light, is equal to substantially 10 ns. Transferring the detection to the next detection point without waiting for the finishing of the fluorescent light generation makes the detection itself impossible.

09678999-100400

Also, it is required to perform the detection with a high-sensitivity that corresponds up to a state where there exist several fluorescent molecules within the spot light size equivalent to the above-described necessary detecting resolution. However, all of the generated fluorescent lights are not detected. Namely, a light utilization efficiency of the detecting optical system and a quantum efficiency of the photomultiplier tube used for the optical detection are not equal to 100%. Moreover, the following values are small: An efficiency with which the excitation light is absorbed in the fluorescent material and a probability with which the absorbed excitation light is converted into the fluorescent light. This requires that the detection be executed by spending a time that is at least tens to hundreds times longer than Δt_L . Furthermore, the more this time is lengthened, the higher the accuracy of a weak light detection becomes which is almost the same as the photon counting.

Also, in order to accomplish such a high-speed characteristic at a practical level, the following conditions are required: Eliminating or reducing influences of foreign substances that are composed of various types of proteins mixed into the DNA chip, or maintaining all the time a focal point of the detecting system onto the inspection plane on which the fluorescent material-added target has been hybridized. Also, in some cases, it becomes necessary to perform

the detection with reference to a plurality of fluorescent lights at a high-speed.

When forming multi-spot lights from a beam emitted from a laser light-source, if the emitted light is wished to be modified into the multi-spot lights without being wasted, i.e., for example, when trying to form 50 multi-spot lights that are 0.04 mm in diameter and are arranged in a line with a pitch of 0.4 mm, the emitted laser beam is formed so that the beam becomes an ellipse-shaped configuration the longitudinal-to-transverse ratio of which is equal to 1 to 50. Irradiating, with the ellipse-shaped beam, a microlens array where microlenses are arranged with a pitch of 0.4 mm makes it possible to obtain the 50 multi-spot lights about 0.04 mm in diameter and having the pitch of 0.4 mm, if a focal length of the microlenses is equal to 60 mm, for example. Since the intensity distribution of the laser beam is Gaussian distribution, in the arrangement of the 50 multi-spot lights formed in the method as described above, spots situated in proximity to the center of the arrangement become lighter and spots situated in proximity to the periphery thereof become darker. Trying to equate as much as possible the intensities of the spots at the center with those of the spots on the periphery requires the following: A spread area of the incoming ellipse-shaped beam should be made large enough as compared with the width of the 50 microlenses. As a

09678652 1.00400

In the DNA probe array, the number of the types of the fixed probes is increased and thus its density is becoming more and more heightened. On account of this, an apparatus for measuring the fluorescent marker distribution of the DNA probe array is expected to operate at the high-speed and with the high-sensitivity in addition to implementing the high-resolution characteristic. In the above-described apparatus, however, no sufficient consideration has been given to this point. Namely, it is required to make the spot diameter of the excitation light more microscopic in order to implement the high-resolution characteristic, whereas the scanning time is increased at that case (when an exposure time for each spot is identical). Moreover, making the spot diameter smaller lessens the number of the fluorescent molecules existing within the spot diameter, thereby lowering the detection sensitivity. Also, in order to implement the high-speed characteristic, it is required to increase the scanning rate or to make larger the spot diameter of the excitation light. Increasing the scanning rate, however, shortens the excitation time for the fluorescent material, thereby lessening the fluorescence intensity or increasing a circuit noise to lower the detection sensitivity. Also, in order to implement the high-sensitivity characteristic, it is required to make

Also, there has been proposed an apparatus by which a plurality of microscopic spots are formed on a sample surface and lights from the plurality of
10 microscopic spots are detected simultaneously (for example, refer to JP-A-11-118446). In this configuration, a light-flux from an excitation light-source is enlarged and a 2-dimensional microlens array is located in the enlarged light-flux so as to form the plurality
15 of irradiation spots, then projecting the spots onto the sample surface. In this case, however, especially when a laser light is used as the excitation light, because of the Gaussian distribution characteristic of the laser beam, the light intensities of spots in
20 proximity to the center are intense and the light intensities of the spots become lower as their positions come nearer to the periphery. Accordingly, it is difficult to equate all the light intensities of the plurality of irradiation spots. This problem is
25 partly solved by enlarging the excitation light up to a light-flux the diameter of which is large enough as compared with the width of the 2-dimensional microlens array. In this case, however, the light utilization

efficiency is no good and the light intensities are decreased, thus resulting in such a problem that the detection sensitivity is deteriorated.

In a method of focusing a one-beam laser
5 light onto a target to be inspected, the detection is executed on a one-pixel by one-pixel basis in a time-sequence manner. As a result, when the fluorescent light is extremely weak, it takes a time to execute the detection equivalent to the one-pixel. Consequently,
10 it takes a considerable amount of time to detect the entire 2-dimensional image. Even if an excitation light of the one-beam laser is strengthened in order to detect the weak fluorescent light emitting target at a high-speed, when trying to detect, for example, $6000 \times$
15 6000 pixels in 1 minute, the detecting time per pixel turns out to become 1 to 2 μsec (microseconds). Executing the detection in such a short time makes it difficult to detect the fluorescent light detection intensity in a broad dynamic range (for example, 2^{16}).
20 Also, since a normal fluorescent material emits the fluorescent light with a delay of 10^{-9} to 10^{-5} sec after receiving the excitation light, the above-described per-pixel fluorescent light detecting time of 1 to 2 μsec prevents the fluorescent light detection from
25 being fully accomplished. Meanwhile, in a method using Nippou disk, the light is utilized effectively only by the amount of a ratio of a microscopic aperture in a uniform light. This condition requires a considerable

REF ID: A64400

amount of time to be spent to detect the weak fluorescent light.

SUMMARY OF THE INVENTION

In order to solve the above-described
5 problems, the present invention provides methods and units described hereinafter.

The inspection of a DNA chip to be inspected is executed in the following steps: Irradiating mutually different positions with a plurality of M
10 excitation lights simultaneously with the use of an objective lens for a time Δt that is longer than a fluorescent light attenuation time, the excitation lights including a spot diameter d that is smaller than a dimension D of each cell, guiding obtained fluorescent lights to a fluorescent light detecting optical
15 path, detecting the fluorescent lights on an image-forming plane that is in a conjugation relationship with irradiation spots onto the DNA chip, and executing the inspection of the DNA chip from positions and
20 intensities of the fluorescent lights. At this time, the spot diameter is set to be substantially $1/N$ of an integer N indicating the cell dimension. Moreover, relative positions between the irradiation spots and the DNA chip are caused to differ j times in sequence
25 so as to inspect the entire inspection target positions $LN^2 = Mj$. Here, L denotes the cell number within the chip. Also, N is made equal to 2 or more and each cell

0967866-100400

is divided into a plurality of portions so as to select and process only significant data out of N^2 data existing within one call, thereby executing the precise inspection. Executing the inspection in this way
5 allows the fluorescent lights to be detected in a time less than $LN^2/(6 \times 10^5)$ sec with reference to the entire inspection target sample-point number LN^2 of the DNA chip.

There are provided M light-receiving aper-
10 tures that have an effective diameter on the image-forming plane that is in the conjugation relationship with the plurality of M irradiation spots onto the DNA chip, the effective diameter being of substantially the same order as an effective diameter of the irradiation
15 spot images. Moreover, an area other than the light-receiving apertures is light-shielded so as to detect the respective lights that have passed through the light-receiving apertures, thereby eliminating noise lights from the irradiation spots or from an area other
20 than the irradiation spot plane so as to perform the inspection having a high signal-to-noise ratio. Also, the M light-receiving apertures that have the effective diameter are optical fiber light-receiving ends, the effective diameter being of substantially the same
25 order as the effective diameter of the irradiation spot images. At the optical fiber light-receiving ends, the lights emitted from optical fiber light-emitting ends are detected, thereby performing the inspection having

09678652-100400

The plurality of M irradiation spots onto the DNA chip are arranged on a straight line with a spacing of substantially kd with reference to the spot diameter d and an integer k . After the irradiation with this spot array during the time Δt has been performed, the spot array is displaced in an array direction by a distance of substantially d , and then the irradiation during the time Δt is performed. This operation is repeated k times in sequence, thereby performing the inspection concerning kM spot positions in the array direction. At the same time, the DNA chip and an inspecting apparatus are relatively displaced at least in a direction perpendicular to the array direction, thereby inspecting a desired 2-dimensional area of the DNA chip. Also, the above-described movement of the spot array is characterized by being performed using an acoustooptic deflector.

The spot array is formed with the microlens array. The spot array can also be formed using a
25 hologram. In synchronization with the above-described movement of the spot array in the array direction, a fluorescent light detection deflecting unit is provided within the fluorescent light detecting optical path so

5

20

25

lens. This allows the excitation lights becoming the noise components to be eliminated from a fluorescent light detection signal.

The above-described M multi excitation spot
5 lights are configured so as to pass through substantially the same position A on the pupil of the objective lens. In addition, the excitation lights reflected regularly on the DNA chip are configured so as to pass through a position B that differs from the
10 position A on the pupil of the objective lens. In this way, a light-shielding member for light-shielding the reflected excitation lights having a desired diameter with B as its center is located on the pupil of the objective lens, or is located at a position that is
15 within the fluorescent light detecting optical path and is conjugated with the pupil of the objective lens. This configuration allows the excitation lights becoming the noise components to be eliminated from the fluorescent light detection signal.

20 Moreover, the reflected excitation lights to be light-shielded are employed as the regularly reflected excitation lights. The excitation lights scattered from the foreign substances within the DNA chip are extracted by being caused to pass through from
25 outside the above-described light-shielding unit or the above-described light-shielding member. Then, the extracted scattered lights are branched off from the above-described fluorescent light detecting optical

09070652 100400

5

15

Employing, as an optical signal storage type
image-pickup unit, a 2-dimensional image-pickup

Also, the above-described excitation lights, which include a plurality of different wavelengths, separate and detect a plurality of fluorescent materials-added different targets. Furthermore, the plurality of fluorescent materials-added different targets are simultaneously irradiated with the excitation lights including the plurality of different wavelengths, thereby separating and simultaneously detecting the different targets. This method makes it possible to detect various types of targets at high-speed.

25 On the inspection plane with which a desired fluorescent material-added target on the above-described DNA chip to be inspected has been hybridized, a second light is obliquely incoming into a proximity

to the above-described excitation spot lights and a position at which the second light is reflected on the inspection plane is detected, thereby detecting the focal point. A relative distance between the inspection plane and the above-described objective lens is controlled in accordance with this focal point information, thereby allowing the focusing to be achieved. Also, the obliquely launched second light is configured so as to pass through the objective lens. This permits the focal point detection and control to be executed with a simplified configuration.

The above-described obliquely launched second light is converted into an S-polarized light toward the detection plane. This enhances a reflectance on the fluorescent light detection plane, thereby making it possible to execute the correct focal point detection. In addition, as the wavelength of the obliquely launched second light, there is employed a wavelength that exerts no excitation to the above-described fluorescent material. This permits the precise detection to be executed without superimposing the noise on the fluorescent light detection signal.

It is an object of the present invention to provide a method and an apparatus therefor that obtain multi-spot lights having a substantially uniform intensity by solving a conventional problem that the light utilization efficiency in the conventional multi-spot light forming method is no good and there exist a

0967863-10400

It is another object of the present invention to provide a method and an apparatus therefor that execute the confocal point detection, the fluorescent light detection and the DNA inspection with the use of the multi-spot lights having the substantially uniform intensity.

Namely, a plurality of N laser beams which travel in substantially the same direction and the adjacent beams of which are in comparative proximity to each other are launched into a polarization component so as to separate each laser beam into two beams of mutually orthogonal polarized components, thereby forming a plurality of $2N$ laser beams. After that, the plurality of $2N$ laser beams are formed into a plurality of $2N$ laser beams which travel in substantially the same direction and the adjacent beams of which are in comparative proximity to each other.

As a concrete method of obtaining such

25 doubled proximate beams, the plurality of N proximate laser beams are launched into the above-described polarization component including a multi-spot lights-doubling prism that has a polarization beam split plane

and total reflection planes. Here, the total reflection planes are parallel to the polarization beam split plane and are positioned at distances of L_1 and L_2 from the polarization beam split plane. This makes it possible to increase the number of the plurality of proximate laser beams up to the doubled number, i.e., $2N$.

Also, the plurality of N proximate laser beams are launched into the above-described polarization component including an anisotropic optical medium. Then, in the anisotropic optical medium, each laser beam is separated into the two beams of the mutually orthogonal polarized components, thereby forming the plurality of $2N$ laser beams. This makes it possible to form the plurality of N proximate laser beams into the plurality of $2N$ laser beams which travel in substantially the same direction and the adjacent beams of which are in comparative proximity to each other.

In addition, the use of the above-described beam-doubling type polarization components in plural number M makes it possible to obtain $2^M N$ laser beams.

The plurality of N proximate laser beams, which are launched into at least one of the above-described one or more of polarization components, are formed into converging laser beams, respectively. This allows the microscopic multi-spot lights to be obtained at a convergence position of the converging laser beams. At this time, the converging laser beams are

096786E2 100400

formed using lenses arranged in plural number, thereby forming the multi-spot lights.

Also, a mask, in which $2^{M'}N$ or more of apertures having a diameter substantially equal to a convergence diameter of the multi-spot lights are arranged with reference to an integer M' satisfying $1 \leq M' \leq M$, is located at the convergence position of the above-described converging laser beams so that the multi-spot lights are focused onto the apertures. This makes it possible to obtain pure microscopic multi-spot lights without the noise lights or stray lights.

The above-described plurality of N laser beams can also be doubled even when the plurality of N laser beams have a $4d$ or less of adjacent spacing pitch with reference to the beam diameter d of the laser beam emitted from the laser light-source or of the semiconductor laser beam formed into a parallel beam. Also, executing the doubling makes it possible to reduce the adjacent beam spacing further down to $1/2^{M'}$. Namely, without using the lens system, it is possible to form the multi-spot lights having the pitch smaller than the diameter d of the laser beam formed into the parallel light-flux.

As a method of forming the above-described plurality of N laser beams, there is provided one or more of 2nd beam-doubling prisms having a cross section of a triangle and a cross section of a parallelogram. Here, the triangle has an oblique side forming an angle

5

10

25

the polarization components or the beam-splitting prisms, one beam is doubled in any one of the beam-doubling methods. On account of this condition, an energy summation of the beams after being split into
5 the two can be made equal to 92% or more of the original beam energy. Besides, even when taking into consideration the reflection losses on the surfaces of the lenses forming the converging laser beams or on the surfaces of the polarization components, 70% or more of
10 the total energy resulting from summing up the respective emitting laser energies can be converted into the total energy of the multi-spot lights.

Furthermore, the reflection losses on the surfaces of the above-described optical components are
15 prevented using an antireflection coat and the like. This method makes it possible to convert, into the total energy of the multi-spot lights, 90% or more of the total energy resulting from summing up the respective emitting laser energies of the laser beams emitted
20 from the one or more of laser light-sources.

In comparison with the conventional method by which the multi spots are formed from the intensities at the various locations of the Gaussian distribution, the splitting of the beam can be made uniform more
25 easily, and the variation in the respective spot energies among the multi-spot lights can be restrained within $\pm 20\%$.

What is more, polarization states of the

09678633-100400

lights incoming into the above-described polarization components are adjusted to the correct states, or a film thickness of a multi-layered film type polarization beam splitter is adjusted to the correct thickness. This allows the intensities of the doubled beams to be substantially equated with each other, thereby making it possible to restrain within $\pm 10\%$ the variation in the respective spot energies among the multi-spot lights.

10 The above-explained 2^M times multiplication of the number of the laser beams makes it possible to form the proximate multi microscopic spots. Thus, the multi-spot lights obtained in this way are used for the confocal point detection, the fluorescent light detection or the DNA detection or the like. This makes it possible to execute the conventionally impossible detection where the light utilization efficiency is high and the variation among the multi-spot lights is small, thereby eventually allowing the confocal point detection, the fluorescent light detection or the DNA detection or the like to be executed at a high-speed and with a high-accuracy.

25 The multi-spot lights formed using the above-described multi-spot light forming methods according to the present invention are projected onto an object to be observed. Then, the lights having been reflected at or having passed through the object to be inspected are caused to pass through multi apertures located at

09678652 100400

positions at which the above-described projected spots are image-formed. Next, the lights having passed through the respective apertures are each detected individually. Executing the confocal point detection in this way makes it possible to execute the confocal point detection where the light utilization efficiency is high and the variation among the multi-spot lights is small, thereby implementing the high-speed and high-accuracy confocal point detection.

10 The multi-spot lights formed using the above-described multi-spot light forming methods according to the present invention are employed as excitation lights, then being projected onto the object to be observed that includes a fluorescent material. Then, 15 fluorescent lights generated by the excitation lights at the object to be inspected are separated from the excitation lights. Next, detectors are located at positions at which the fluorescent lights generated at the excitation light-projected spots are image-formed, 20 thereby detecting the fluorescent lights at the positions of the respective multi-spot lights. This allows the plurality of positions to be simultaneously irradiated with the excitation lights with a high-intensity. Also, since the variation among the respective spots is small, it becomes possible to execute a 25 high-speed and high-accuracy fluorescent light detection.

In the above-described fluorescent light

0967852.100400

09678652 100400

detection, the fluorescent lights are caused to pass through multi apertures located at the positions at which the fluorescent lights generated at the excitation light-projected spots are image-formed. In addition, there are located the detectors for individually detecting the fluorescent lights having passed through the respective apertures. This eliminates fluorescent lights other than the fluorescent lights generated by the excitation lights at the object to be observed, thereby making it possible to execute a fluorescent light detection having a high signal-to-noise ratio.

The multi-spot lights formed using the above-described multi-spot light forming methods according to the present invention are employed as the excitation lights, then being projected onto the object to be observed that includes a fluorescent material-added DNA. The target to be observed is implemented in the following way: A known probe DNA is attached to a predetermined position on a substrate such as a glass, and a target DNA is poured onto the glass substrate so as to hybridize the target DNA corresponding to the nucleotide sequence of the probe DNA, thus implementing the object to be observed. Here, the target DNA is formed by adding the fluorescent material to an end of the DNA purified and amplified from a living body sample, i.e., a target to be inspected. The excitation lights of the multi-spot lights are irradiated with the

In the above-described DNA inspection, the fluorescent lights are caused to pass through the multi apertures located at the positions at which the fluorescent lights generated at the excitation light-
15 projected spots are image-formed, then individually detecting the fluorescent lights having passed through the respective apertures. This makes it possible to detect the fluorescent light intensities at the
20 positions of the respective multi-spot lights so as to inspect the DNA, thereby being capable of executing the DNA inspection having an even higher signal-to-noise ratio.

In the fluorescent light detection and the
25 DNA inspection, in many cases, a wavelength of the
excitation lights and that of the fluorescent lights
come comparatively close to each other. The use of the
multi-spot lights in such a case enlarges the fields-

In order to solve the above-described
20 problem, in the method of separating the fluorescent
lights from the excitation lights, in addition to still
using the wavelength separating beam splitter, the
image-forming optical system is replaced by a
telecentric image-forming optical system. In the
25 telecentric image-forming optical system, primary
light-rays of the fluorescent lights become parallel to
each other, the fluorescent lights being generated from
the respective spots extending from the image-forming

optical system to the image-formed positions through
the excitation by the respective multi-spot lights.
Moreover, the interference filter and/or the wavelength
separating beam splitter are inserted between the
5 telecentric image-forming optical system and the image-
forming positions. This method causes the fluorescent
light generated from whatever spot excitation light to
be launched into the interference filter or the wave-
length separating beam splitter at an incident angle
10 that is common to all the fluorescent lights. As a
consequence, concerning the fluorescent light from
whatever spot and the excitation lights becoming the
noise components as well, it becomes possible to select
the fluorescent lights and to eliminate the excitation
15 lights under the same condition, i.e., under an optimum
condition. This situation allows the fluorescent light
detection to be executed with an extremely small amount
of the excitation light leakage, i.e., with an
extremely small amount of the noise. As is seen from
20 the above-described explanation, the use of this
fluorescent light detecting method further makes it
possible to perform, precisely and with a high-
accuracy, the DNA inspection where it is required to
detect the fluorescent lights the intensities of which
25 are exceedingly weaker as compared with the intensities
of the reflected excitation lights.

It is an object of the present invention to
provide a distribution measuring apparatus for measur-

00400T 233330

ing the fluorescent marker distribution in the DNA probe array and the like, the distribution measuring apparatus being capable of solving the conventional problems and accomplishing the high-resolution performance and the high-speed characteristic at the same time.

The fluorescent marker distribution measuring apparatus according to the present invention and accomplishing the above-described object is an apparatus for scanning and reading a light-emission pattern from the fluorescent marker captured on a sample surface on a substrate. The fluorescent marker distribution measuring apparatus is characterized by including the following configuration components: A stage for mounting thereon the substrate of a target to be read, a unit for forming a plurality of irradiation spots on the sample surface on the substrate with a specified spacing that is larger than a diameter of the irradiation spots, a movement mechanism for moving the stage, a converging/detecting unit for converging and detecting light-emissions generated from the plurality of irradiation spots on the sample surface, a control unit for controlling the movement mechanism so that the substantially entire surface of the sample surface is irradiated in correspondence with the formation positions of the plurality of irradiation spots, and a processing unit for processing a signal from the converging/detecting unit so as to reconstruct images

09678692-100400

on the sample surface. The intensities of the plurality of irradiation spots are set to be substantially almost equal to each other.

The unit for forming the plurality of
5 irradiation spots can be configured as follows: The unit includes at least one laser light-source as excitation light-sources. Moreover, the unit splits a light emitted from an excitation light-source so as to image-form the irradiation spots in such a manner that
10 the irradiation spots are arranged on the sample surface and a spacing of adjacent irradiation spots becomes smaller than 1mm. The unit for splitting the light emitted from the excitation light-source can be configured as the splitting prism, the optical anisotropic medium, the optical fiber, a polarization mirror
15 or a combination of these devices.

The unit for forming the plurality of irradiation spots can also be configured as follows: The unit includes N ($N \geq 1$) excitation light-sources and
20 M -stage 2-splitting units ($M > 2$), and forms $N \times 2^M$ irradiation spots. As the 2-splitting unit, there can be employed the splitting prism, the optical anisotropic medium, the optical fiber or the polarization mirror.

25 The unit for forming the plurality of irradiation spots can also be configured as follows: The unit includes a plurality of laser light-sources and a plurality of optical fibers. Furthermore, light-

004007 25984960

emitting ends of the plurality of optical fibers are located on a straight line, thereby forming the plurality of irradiation spots.

It is preferable that the plurality of
5 irradiation spots should be positioned on a straight line with a substantially fixed spacing.

The converging/detecting unit converges and, almost simultaneously, detects a plurality of fluorescent emitted lights generated from the plurality of
10 irradiation spot-portions. The unit includes a wavelength selecting filter so as to separate fluorescent components from excitation components out of the emitted lights generated from the plurality of irradiation spot-portions, then detecting the fluorescent
15 components. The converging/detecting unit can also be configured as follows: The unit has pinholes at which the emitted lights generated from the plurality of irradiation spot-portions are image-formed, then detecting the lights passing through the pinholes, the
20 pinholes the number of which being the same as that of the irradiation spot-portions.

The control unit makes it possible to measure the entire plane of the sample surface by the following method: Employing, as a unit, step-like movements on a
25 first microscopic width basis at n times and a step-like movement on a second width basis at one time subsequent thereto, the second width being greater in comparison with the first microscopic width, the stage

09678652 100400

is displaced in a specified one-axis direction. Then, this process is repeated, thereby scanning the sample surface. More concretely, the control unit is capable of controlling the stage movement so that the following operation is implemented: Employing, as the unit, (n-1)-times step-like style movements on the basis of a width of $1/n$ (n: an integer) of the irradiation spot spacing and the subsequent one-time step-like style movement on the basis of (a width between both ends of the excitation spot group + the first width), the movement in the irradiation spots-arranged direction is executed, and this process is repeated thereby scanning the sample surface.

It is desirable that fetching of the signal from the converging/detecting unit should be executed while the stage is being displaced in a direction perpendicular to the plurality of irradiation spots-arranged direction.

The unit for forming the plurality of irradiation spots is required to form the plurality of irradiation spot-portions simultaneously. In order to image-form the lights onto the sample surface, there is employed a condenser lens the data of which is as follows: The numerical aperture is 0.7 or more, the effective field-of-view is 1.0 mm or more, and the difference between the sample surface and the lens tip is 0.7 mm or more.

The unit for forming the plurality of

09678652 100400

irradiation spots can also be configured as follows:
The unit includes a plurality of optical anisotropic
media the lengths of which in the optical axis direc-
tion differ from each other or a plurality of optical
5 anisotropic media the crystalline-axis directions of
which differ from each other, and a plurality of
wavelength plates located between the adjacent optical
anisotropic media.

The unit for forming the plurality of
10 irradiation spots can also be configured as follows:
The unit includes a device where the plurality of
optical anisotropic media and the plurality of wave-
length plates are located alternately. Moreover, a
length of each optical anisotropic medium in the light-
15 travelling direction is equal to about one-half of a
length of an optical anisotropic medium located
immediately preceding thereto.

The unit for forming the plurality of
irradiation spots may also be configured as follows:
20 The lights from the excitation light-sources are
scanned and launched in sequence into one ends of a
plurality of aligned optical fibers, and light-emitting
ends of the optical fibers are located on a straight
line, thereby forming the plurality of irradiation
25 spots.

Also, it is preferable that there should be
provided a function of executing an intensity correc-
tion for each detection signal of the respective

09678693 100400

It is an object of the present invention to provide a technology for detecting weak fluorescent lights at a high-speed, with a high-resolution and with a high-sensitivity with reference to a target to be detected that requires 2-dimensional large number of lines of resolution. Also, It is another object thereof to provide, using this technology, a technology for inspecting a DNA with a high-sensitivity and at a high-speed.

The target object having a fluorescent characteristic is irradiated with multi-spot excitation lights including a large number of M microscopic spots. Fluorescent lights generated by the excitation lights from the respective multi spots are separated from the excitation lights. Then, fluorescent light images emitted from the target object are detected using a plurality of weak light detecting devices allowing the photon counting to be executed. This makes it possible to detect even an extremely weak fluorescent light. Photon signals obtained from the respective detecting devices are each photon-counted individually, then individually storing the photon-counted numbers N_{pm} detected by the respective detecting devices. In addition, positions of the multi-spot lights and a

position of the target object are changed relatively using a driving system and the like, then storing in sequence the photon-counted numbers from the respective detectors. Storing and collecting in this way the
5 photon-counted number data over a desired range on the target object makes it possible to construct the fluorescent light picture from the collected data.

Also, sheet-shaped excitation lights are used instead of the above-described multi-spot lights.

10 Fluorescent lights, which have been generated from irradiation areas obtained by the irradiation with the sheet-shaped excitation lights and having a long and narrow configuration, are separated from the excitation lights. Then, fluorescent light images emitted from
15 the target object are detected using the plurality of weak light detecting devices allowing the photon counting to be executed. Photon signals obtained from the respective detecting devices are each photon-counted individually, then individually storing the photon-
20 counted numbers N_{pm} detected by the respective detecting devices. In addition, positions of the irradiation areas resulting from the sheet-shaped excitation lights and having the long and narrow configuration and the position of the target object are changed relatively,
25 then storing in sequence the photon-counted numbers from the respective detectors. Storing and collecting in this way the photon-counted number data over a desired range on the target object makes it possible to

09678852-100400

construct the fluorescent light picture from the collected data.

By executing the irradiation with the multi-spot lights or the sheet-shaped excitation lights and
5 detecting the fluorescent lights from M pixels simultaneously, it becomes possible to spend a time of M to 2M μ sec per pixel in the case of trying to detect the 6000 \times 6000 pixels in 1 minute. Here, the case has been described previously in the conventional problems.
10 For example, assuming M = 50, this time becomes equal to 50 to 100 μ sec. This condition makes it possible to solve the previously-described problem concerning the delay in the fluorescent light generation. Also, the following reason permits the dynamic range to be
15 ensured and the high-sensitivity detection to be executed.

Namely, the previously-described per-pixel detecting time of the order of 1 μ sec shortens a detecting time that is long enough for a photo counting
20 measuring time needed to execute the high-sensitivity detection, thereby making it difficult to ensure the dynamic range. This is attributed to the fact that, since the pulse-width of a photon pulse signal generated when one photon is detected is equal to tens
25 of n seconds, only a signal of, at most, tens of pulses can be detected within the time of 1 μ sec. Also, even if, in such a short time, an attempt is made to detect the fluorescent light intensity in an analogue manner,

09678652-100400

frequency characteristics of the detecting circuit make it difficult to execute the detection in a state where a sufficient dynamic range has been ensured.

Employing, as the above-described target
5 object, a sample obtained from coupling a fluorescent molecule-added DNA fragment with a DNA corresponding thereto, the inspection is executed in the following way: In the case where the target to be inspected is, as an example, a DNA chip, a target that results from
10 adding a desired fluorescent material to a DNA fragment formed from the target to be inspected, i.e., a DNA, is hybridized with the DNA chip at first. Then, the hybridized DNA chip to be inspected is irradiated with the multi-spot excitation lights including the large
15 number of M microscopic spots. Fluorescent lights obtained by the irradiation from the multi spots are separated from the excitation lights. Next, separated fluorescent light images emitted from the DNA chip are detected using the plurality of weak light detecting
20 devices allowing the photon counting to be executed. Moreover, photon signals obtained from the respective detecting devices are each photon-counted individually, then individually storing the photon-counted numbers N_{pm} detected by the respective detecting devices. In
25 addition, positions of the multi-spot lights and a position of the DNA chip are changed relatively, then storing in sequence the photon-counted numbers from the respective detectors. In this way, the photon-counted

004007 25987960

5 The use of the sheet-shaped beams instead of
the multi-spot lights also makes it possible to execute
the DNA inspection by detecting the fluorescent
material added to the target DNA in much the same way
as explained in the above-described fluorescent light
10 detection using the sheet-shaped beams.

A multi-spot aperture or a long and narrow aperture that permits only a multi-spot image or a sheet-shaped long and narrow area image to pass through is located at a focal point achieving position of fluorescent light images from the above-described target object surface, thereby performing the confocal point detection, the focal point achieving position being situated at a position at which the diameters of the multi-spot excitation lights or the sheet-shaped excitation lights with which the target object is irradiated become minimum-focused diameters. This makes it possible to obtain the confocal point image having a high signal-to-noise ratio. Namely, it becomes possible to detect, without being subjected to the influence from a fluorescent light noise and thus with a low-noise, the fluorescent lights at the multi-spot positions to be detected or the fluorescent lights at the sheet-shaped beam positions to be detected.

Here, the fluorescent light noise exists in the background of substances such as a fluorescent material existing in optical paths other than the above-described positions to be detected. If the sample
5 toward which the fluorescent light detection is performed exists within a 2-dimensional plane, relative positions between the multi spots and the sample are changed within the plane, then performing the confocal point detection. This method allows the high signal-
10 to-noise ratio fluorescent light detection or DNA inspection to be executed in a state of being scarcely subjected to the influence of a noise by a fluorescent material existing outside the plane.

In the above-described fluorescent image
15 detection using the multi-spot lights, the relative positions between the multi spots and the sample are changed in at least one direction out of three directions in total, i.e., two directions within the target object surface and the remaining one direction
20 perpendicular to the target object surface. In particular, in the case of the above-described confocal point detection, the relative position of the target is changed in the optical axis direction from the position at which the diameters of the multi spots or the sheet-
25 shaped beams become the minimum-focused diameters, then determining the focal point achieving position from the obtained variation in the fluorescent light image intensity. Accordingly, from the fluorescent light

00400T" 2992360

intensity at this position and toward a target having irregularity on its surface, it becomes possible to obtain the accurate fluorescent light intensity information, surface irregularity information, or information on the 3-dimensional positions emitting the fluorescent lights.

As having been pointed out in the problem in the case of the above-described conventional one-spot excitation light, the larger the number of the multi-spot lights becomes, the more advantageous it becomes to detect the fluorescent light image at a high-speed. Setting M to be 10 or larger increases, up to hundreds, the maximum photon-counted number detectable within this time, thereby becoming effective in implementing the high-sensitivity characteristic and the broad dynamic range. Since an even higher-speed characteristic is implemented in the DNA inspection and the like, providing the plurality number of spots exhibits an outstanding effect. Making M equal to 50 or more exhibits a more outstanding effect. Namely, setting M to be 50 or larger makes it possible to detect, for example, the 6000×6000 pixels in spending tens of μ seconds per pixel, thereby allowing all the pixels to be detected within 1 minute.

The above-described multi spots are arranged on a 1 or 2-dimensional straight line in order to accomplish the following purposes: Detecting the multi spots using a plurality of detecting devices, above

00000000 00000000 00000000 00000000

The relative positions between the multi-spot excitation lights or the sheet-shaped excitation lights and the target are changed, and a period during which this movement by the amount of one pixel is executed is set to be T_d . At this time, a value $\alpha T_d / \Delta t_0$ is determined as follows: First, a value $T_d / \Delta t_0$ is determined by dividing the period T_d by Δt_0 . Here, Δt_0 denotes the pulse-width of the previously-described photon counting signal at the time of detecting a single photon. Then, the value $\alpha T_d / \Delta t_0$ is determined by multiplying $T_d / \Delta t_0$ by a desired coefficient α that is larger than 0.1 and smaller than 1. Moreover, employing, as a judging criterion, a condition that this value has reached the above-described photon-counted number N_{pm} , i.e., at the time of $\alpha T_d / \Delta t_0 \geq N_{pm}$, the detection is executed in a state of weakening the fluorescent light detection intensities so that the photon counting becomes executable. This weakening is performed using such a method as changing the intensities of the multi-spot excitation lights or the sheet-shaped excitation lights. Namely, in the point of the accuracy, it is impossible to execute the photon

counting that is more than α times as large as the value obtained by dividing the per-pixel detecting time by the photon pulse time-width. Accordingly, in the following way, the photon counting value is adjusted to the value toward which the photon counting is effectively executable: Weakening the excitation lights, shortening the excitation light irradiation time to effectively lower the excitation light intensities, or lowering the gain of the detecting device so as to weaken the detected fluorescent lights.

The above-described multi-spot excitation lights or sheet-shaped excitation lights are converted into multi-color lights having 2 or more of wavelengths. This increases the information on the fluorescent light detection, thereby enhancing the fluorescent light detecting function and the DNA detecting function.

Also, a time during which the above-described photon pulse signal is being positioned at a high level is addition-measured during a time βT_d that is less than the per-pixel detecting time T_d . When setting the value of this time to be T_h' , it is judged whether or not a condition $T_h' \geq \gamma \beta T_d$ is satisfied with reference to a predetermined γ that is smaller than 1. If this inequality should be satisfied, there is employed a result obtained by integrating the output signal from the detecting device in an analogue-style integrating circuit. This makes it possible to perform

00400T 2332960

laser resonator, the reflectance of a mirror at the emitting window is set to be substantially 90%, and the remaining substantially 10% is extracted as the emitting light. The reflectance at the emitting window is made equal to 100% so as to confine the light within the resonator, and the hologram is located in an optical path within the resonator. This method allows substantially 10% of the hologram's diffraction efficiency to be utilized as the multi-spot lights or the sheet-shaped beams. As a result, it is possible to obtain the multi-spot lights or the sheet-shaped beams the intensities of which are almost 10 times higher as compared with those in the conventional case where the hologram is located in a laser-emitting optical path. Consequently, it becomes possible to execute the high-speed and high-sensitivity fluorescent light detection and DNA inspection.

The present invention permits a laser light emitted from a laser light-source to be converted into the multi-spot lights with an exceedingly high-efficiency and without being wasted. At the same time, the present invention makes it possible to extremely lessen the variation among the respective multi-spot lights. As a consequence, using the multi-spot lights, it becomes possible to execute the high-speed and high-accuracy confocal point detection. Also, using the multi-spot lights, it becomes possible to execute the high-speed and high-accuracy fluorescent light detec-

004007 25987950

tion and DNA inspection.

09678663-100400
004007-25984960

The present invention allows even the analogue integrating detection to be executed, thereby making it possible to execute the detection having a
5 exceedingly broad dynamic range. Namely, it becomes possible to even detect the fluorescent light image of, for example, the 6000×6000 pixels in the dynamic range of 2^{16} in the detecting time of 1 minute. As a result, it becomes possible to detect targets to be inspected,
10 such as the DNA chip, in the detecting time of an order of 1 minute. This eventually makes it possible to detect, in a short time and precisely, a large quantity of samples to be inspected that are collected in a widely executed group checkup.

15 Also, the present invention is not only applied to the DNA inspection, but is widely used for a fluorescent light detecting microscopic method. The present invention tremendously shortens the times that have been required for the conventional observations
20 and inspections. Namely, it becomes possible to detect, in a short time, even a weak light toward which only several photons can be detected. Also, it becomes possible to execute, in a short time and with a high-accuracy, the detection over a broad range ranging from
25 the weak light to the strong light to be detected.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a diagram for illustrating an

receiving apertures on the fluorescent light detection plane in the embodiment in FIG. 1;

FIG. 11 is an embodiment-illustrating diagram in the present invention, where the multi spots are
5 formed using a hologram;

FIG. 12 is a diagram for illustrating a method of creating the hologram in FIG. 11;

FIG. 13 is a diagram for illustrating another embodiment in the present invention;

10 FIG. 14 is a diagram for illustrating a 2-dimensional multi-spot generating microlens array used in the embodiment in FIG. 13;

FIG. 15 is a diagram for indicating a characteristic of the wavelength separating beam
15 splitter in the embodiments in the present invention;

FIG. 16 is a diagram for indicating a characteristic of an interference filter in the embodiments in the present invention;

FIG. 17 is an embodiment-illustrating diagram
20 in the present invention, where excitation lights are light-shielded using a space filter;

FIG. 18 is a diagram for illustrating the space filter in FIG. 17;

FIG. 19 is another embodiment-illustrating
25 diagram in the present invention, which is a diagram for illustrating an excitation light light-shielding method utilizing the polarization;

FIG. 20 is an embodiment-illustrating diagram

09678652 100400

FIG. 36 is an enlarged explanatory diagram

for explaining the embodiment in FIG. 35;

FIG. 37 is an enlarged explanatory diagram
for explaining the embodiment in FIG. 35;

FIG. 38 is a diagram for indicating the move-
5 ment of the multi spots in the embodiment in FIG. 35;

FIG. 39 is a diagram for indicating the move-
ment of a DNA chip chuck in the x direction in the
embodiment in FIG. 35;

FIG. 40 is a diagram for indicating the move-
10 ment of the DNA chip chuck in the y direction in the
embodiment in FIG. 35;

FIG. 41A is a front view for illustrating the
configuration of an embodiment of the multi-spot light
forming unit according to the present invention;

15 FIGS. 41B, 41C, and 41D are partially
enlarged diagrams of FIG. 41A;

FIG. 42 is a front view for illustrating the
configuration of an embodiment of the multi-spot light
forming unit according to the present invention;

20 FIG. 43 is a front view for illustrating an
embodiment of a mask according to the present
invention;

FIG. 44 is a front view for illustrating the
configuration of an embodiment of the multi-spot light
25 forming unit according to the present invention;

FIG. 45 is a perspective view for illustrat-
ing the configuration of an embodiment of the fluo-
rescent light detecting and DNA inspecting apparatus

004007 2592960

according to the present invention;

FIG. 46 is a front view for illustrating an embodiment of the multi-spot light forming unit according to the present invention;

5 FIG. 47 is a front view for illustrating an embodiment of a 2-dimensional multi-spot light forming unit according to the present invention;

FIG. 48 is a front view for illustrating an example of the arrangement of the 2-dimensional multi-
10 spot lights according to the present invention;

FIG. 49 is a front view for illustrating an embodiment of a confocal point detecting apparatus according to the present invention;

FIG. 50 is a diagram for indicating the
15 relationship between the multi-spot lights and stage scanning in the confocal point detection according to the present invention;

FIG. 51 is a schematic diagram for illustrating the entire configuration of one embodiment of a
20 fluorescent marker distribution measuring apparatus according to the present invention;

FIG. 52 is a diagram for illustrating the configuration of an embodiment of a multi light-source distribution unit according to the present invention;

25 FIG. 53 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit according to the present invention;

0967863-100400

FIG. 54 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit according to the present invention;

5 FIG. 55 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit according to the present invention;

10 FIG. 56 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit according to the present invention;

15 FIG. 57 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit according to the present invention;

FIG. 58 is a diagram for illustrating the configuration of an embodiment of a multi-detection unit according to the present invention;

20 FIG. 59 is a diagram for illustrating the configuration of another embodiment of the multi-detection unit according to the present invention;

25 FIG. 60 is a diagram for illustrating the configuration of another embodiment of the multi-detection unit according to the present invention;

FIG. 61 is a diagram for illustrating the configuration of another embodiment of the multi-detection unit according to the present invention;

09678652 100400

FIG. 62 is a diagram for illustrating the configuration of another embodiment of the multi-detection unit according to the present invention;

FIG. 63 is a diagram for illustrating the
5 configuration of another embodiment of the multi-detection unit according to the present invention;

FIG. 64 is a diagram for illustrating an example of images detected;

FIG. 65 is an explanatory diagram for
10 explaining an example of the displacement of an XYZ driving unit 20f;

FIGS. 66A, 66B are diagrams for illustrating displacement curves of x, y axes of the XYZ driving unit 20f;

FIG. 67 is a diagram for illustrating the
15 configuration of another embodiment of the multi light-source distribution unit according to the present invention;

FIG. 68 is a diagram for illustrating the
20 configuration of another embodiment of the multi light-source distribution unit according to the present invention;

FIG. 69 is a diagram for illustrating the
configuration of another embodiment of the multi light-
25 source distribution unit according to the present invention;

FIG. 70 is a perspective view for illustrating the schematic configuration of the DNA chip

09678653-100400

inspecting apparatus according to the present invention;

FIG. 71 is a plane view for indicating the relationship between cells of the DNA chip and the
5 excitation lights;

FIG. 72 is a diagram for explaining the scanning of the DNA chip in the x, y directions according to the present invention;

FIG. 73 is a diagram for indicating the relationship between the scanning of the DNA chip in the x direction and photon detection according to the present invention;

FIG. 74 is a diagram for illustrating photon counting signals of weak lights;

15 FIGS. 75A to 75D are diagrams for illustrating photon pulse signals in the case of strong detected lights;

FIG. 76 is a block diagram for illustrating a circuit configuration for detecting a broad dynamic range according to the present invention;

FIGS. 77A to 77E are diagrams for indicating a method of differentiating between the weak detected lights and the strong detected lights according to the present invention;

25 FIGS. 78A, 78B are diagrams for indicating a
method of detecting even stronger detected lights
according to the present invention;

FIG. 79 is a plane view of the cells of the

DNA chip for illustrating the case where there are employed the sheet-shaped excitation lights according to the present invention; and

FIG. 80 is a perspective view of a portion of an optical system for illustrating an embodiment where the multi spots according to the present invention are formed by a hologram within a laser resonator.

DESCRIPTION OF THE EMBODIMENTS

FIG. 1 is a diagram for illustrating an embodiment in the present invention. The reference numerals denote the following configuration components:

1 A multi-spot excitation lights-irradiating system for forming multi-spot excitation lights to irradiate a DNA chip 2 with the excitation lights so that a fluorescent light detection can be executed, 3 a fluorescent light detecting system for detecting fluorescent lights generated by the multi-spot excitation lights, 11 an excitation light-source including an excitation light light-source and an excitation light beam forming optical system. A He-Ne laser light beam is formed into a desired longitudinal-to-transverse ratio of the beam diameter by two cylindrical lenses having different focal lengths, then being launched into an AO deflector 12 through a mirror 1000. The AO deflector 12 includes a terminal of a frequency- ω high-frequency voltage applied to a quartz oscillator, and an input terminal of an amplitude signal the frequency

09678653 100400

ω_v of which is lower than the frequency ω .

The signal with the frequency ω , which is transmitted from a control apparatus 4, has a frequency band in a range of $\omega \pm \omega_0$. Changing the frequency results in a change in the diffraction angle of the excitation light incoming into the AO deflector 12. Also, an inputting of the amplitude signal ω_v from the control apparatus 4 brings about a change in the diffraction efficiency, thereby making it possible to control the diffraction light intensity. The diffraction light having passed through the AO deflector is separated from its 0th light (not illustrated) (the 0th light is light-shielded). Then, a lens system 13 including two lenses 131, 132 of focal lengths f_1 , f_2 irradiates a microlens array 14 with the separated diffraction light in a desired beam diameter. Changing the frequency of the AO deflector 12 changes the angle of the excitation light incoming into the microlens array 14, but causes no change in the position thereof.

FIG. 4 is an enlarged detailed view of the microlens array 14. Microscopic microlenses composed of glass are arranged in a 1-dimensional configuration in a large number of 32 to 256. Let's explain the light incoming therein: For example, lights 1010 represented by solid-lines pass through the respective microlenses 141, 142,, then image-forming microscopic spots 111, 112,, 11M on a straight line ℓ on a focal point plane Σ . As illustrated by

00400T" 25924950

5

10

20

The reason why one cell is divided into a plurality of pixels is as follows: When a foreign substance such as a protein is mixed in one cell, in

some cases, an excitation light incoming into this protein generates a large-intensity fluorescent light. The dimension of such a foreign substance is usually equal to, at most, several μm . Accordingly, if the pixel dimension is equal to several μm and the cell dimension is equal to 10 μm for example, and if a method as described later allows the foreign substance position to be detected and be separated within the cell of 10 μm , it becomes possible to precisely determine the magnitude of the fluorescent light in accordance with the information on a portion other than the foreign substance portion.

FIG. 3 illustrates a side view of the DNA chip. The configuration given in this drawing is that the hybridized targets are mounted in a state of being naked on a glass substrate. This state is presented in some cases, and there are other cases where, as will be described later, the hybridized targets are sandwiched between glass substrates. In any case, the microscopic excitation light spots are converged onto the plane on which the targets exist. The light-converged diameter is substantially equal to the dimension of the pixel to be detected, i.e., the square-shaped minimum unit illustrated in FIG. 2.

At the initial frequency of the AO deflector 12, there has been obtained the diffraction light represented by solid-lines in FIG. 1. At this time, as illustrated in FIG. 3, the pixels 201, 202, 203,,

00400T"2987960

allows fluorescent lights to be detected from the

Moreover, after the lapse of $60 \mu s$, changing the frequency of the AO deflector 12 gives rise to the change in the diffraction angle of the excitation light. Then, as illustrated in FIG. 1 and FIG. 4, lights $10j_20$ denoted by dotted-lines are launched into the microlens array 14. As a result, as illustrated in FIG. 3, the DNA chip is irradiated with the excitation light spot array as indicated by $111, 112, 113, \dots, 11M$. This irradiation allows fluorescent lights to be detected from pixels $211, 212, 213, \dots, 21M$. In this way, the irradiation with the M multi spots is executed in sequence with a shift on a pixel-pitch basis. When the shifts by the amount of j pixels have been finished, it turns out that the fluorescent lights by the amount of jM pixels have been detected all.

25 Next, referring to FIG. 1, the explanation
will be given below concerning the embodiment of the
fluorescent light detection. A beam splitter 30
located between the lens 15 and the objective lens 16

is a wavelength separating beam splitter. In the present embodiment, the wavelength of the He-Ne laser light from the excitation light-source is equal to 633 nm. The fluorescent material added to the targets on the DNA chip is Cy5, and the wavelength of the fluorescent lights to be detected lies in proximity to 670 nm.

The wavelength separating beam splitter 30 permits the 45°-incident excitation light at the wavelength of 633 nm to pass through by substantially 100%, and causes the 45°-incident fluorescent lights at the wavelength of 670 nm to be reflected by substantially 100%. The beam splitter, however, reflects the 633 nm excitation light as well by a exceedingly slight amount. The exceedingly slight amount of reflection becomes a problem since the fluorescent lights are extremely weak. Accordingly, in the embodiment in FIG. 1, an interference filter 34, which has its central wavelength characteristic at 670 nm and the half-value width of which is equal to about 15 nm, is inserted into the fluorescent light detecting system 3 so as to cause the interference filter to light-shield the excitation light leakage. Incidentally, the component 34 is not limited to the interference filter. Thus, it is allowable to use so-called a color filter for permitting a certain value or more of wavelength light to pass through and causing a certain value or less of wavelength light to be light-shielded. Also, the

004001 2597950

combined use of the color filter and the interference filter is allowable. Hereinafter, the explanation will be given concerning the embodiments, using the interference filter alone for the simplicity of the explanation.

Next, the explanation will be given below concerning the following: Changes in the positions of detected fluorescent light images when the positions of the multi-spot excitation lights on the DNA chip are changed using the AO deflector, and corrections of the position changes needed in order to execute the detection with the fixed detector. The wavelength separating beam splitter 30 in FIG. 1 performs the corrections of the position changes as well. FIG. 5 illustrates the main portion in FIG. 1, and the same reference numeral as that in FIG. 1 denotes the same component. The wavelength separating beam splitter 30 is driven by a piezo device 301 having a high resonant frequency characteristic of 5 to 10 kHz, and is configured to perform a microscopic rotation with the y axis as its center.

FIGS. 6A to 6E and FIG. 7 are diagrams for explaining the role of this microscopic rotation, and the same reference numeral as that in FIG. 1 denotes the same component. By the deflection signal inputted into the AO deflector 12 from the control apparatus 4, the respective positions of the multi excitation microscopic spots 1011, 1021,, 10M1 on the DNA

09678652 100400

chip 2 in FIG. 6C are changed to 1012, 1022,, 10M2 in sequence on the one-pixel basis. At this time, assuming that the wavelength separating beam splitter 30 performs no rotation, as illustrated in FIG. 6D, multi fluorescent light points 1211, 1221,, 12M1 on a fluorescent light detection plane Σ_{PH} that is located at a position conjugated with the DNA chip are changed to 1212, 1222,, 12M2 on the one-pixel basis as well.

10 The fluorescent light spot image 1212 on the fluorescent light detection plane, as illustrated in the drawings, is image-formed as a 1212 point onto an end of one optical fiber in an optical fiber bundle 322 by a fluorescent light detecting microlens array 321, 15 then being launched into the one optical fiber. The one optical fiber is formed of a core 3221 through which a light passes and a portion 3222 for protecting the core. The diameter of the core through which the light passes is somewhat larger than that of the 20 (multi) fluorescent light point 1211 on the fluorescent light detection plane Σ_{PH} . If, however, the wavelength separating beam splitter 30 performs no rotation, the 1211 point is displaced to 1212, 1213, 1214 (FIG. 6E) by the driving of the AO deflector 12, then being 25 shifted from the optical fiber light-receiving end. This makes the detection impossible. Accordingly, as illustrated in FIG. 7, using the piezo device 301 having the high resonant frequency characteristic, the

0040400 2598450

wavelength separating beam splitter 30 is driven so that it performs the microscopic rotation.

Namely, in FIGS. 6A to 6E in the case of no microscopic rotation, the fluorescent light microscopic spot image 1211 is displaced to the different locations 1212, 1213, 1214. On the other hand, as illustrated within a dotted-line frame in FIG. 7, driving the beam splitter to perform the microscopic rotation permits the spot to come onto substantially the same position on the plane Σ_{PH} .

FIGS. 8A to 8F illustrate the relative time variations among the following respective signals: S_{A12} , an ON-OFF signal or an intensity modulation signal of the above-described AO deflector 12, S_{B12} , the deflection signal of the AO deflector 12, S_{30} , a driving signal of the piezo device 301 for deflection-driving the wavelength separating beam splitter 30, S_{33K} , a fluorescent light detection signal detected by one k-th photomultiplier tube 33 through a fiber 32, S'_{33K} , a per-pixel image storage (integration) signal of the fluorescent light detection signal, and S''_{33K} , a per-pixel final result of this image storage (a value obtained by a sampling-and-holding of S'_{33K} at a point-in-time before the image storing has been performed and the multi-spot excitation lights transfer to the excitation of the next pixel). In the embodiment of this graph, the multi-spot excitation lights are shifted in sequence on the one-pixel basis by the AO

00400T 2598950

deflector 12, and in this way, one spot has been shifted in sequence by the amount of ten pixels.

In order to enhance a signal-to-noise ratio in the detection of each pixel, the number of this shifting need to be equal to 2 or more. The larger the number is, the more desirable it is to implement the enhancement of the signal-to-noise ratio. However, conditions such as restrictions on the apparatus's configuration components naturally impose an upper limit on the number. Nevertheless, making the number equal to 5 or more outstandingly reduces the influences of the scattered lights or the fluorescent lights accompanied by the foreign substance irradiation with the adjacent multi-spot excitation lights halfway in the optical paths.

As illustrated in FIGS. 8A to 8F, the frequency (the frequency of an ultrasound applied to an ultrasound quartz oscillator, i.e., the deflection angle of the deflector) signal S_{B12} of the AO deflector 12 is changed in sequence in a step-like manner. During this change, the driving signal S_{30} of the piezo device 301 for deflection-driving the wavelength separating beam splitter 30 is changed linearly in response to this change. The AO deflector 12 diffracts a light by an extremely slight amount of change of a transparent medium's refractive index caused by the ultrasound propagation. Meanwhile, the piezo device 301 drives the beam splitter 30 as a whole. As a

09678652-100400

result, there exists a difference in the frequency response characteristic between them. Consequently, the fast frequency signal S_{B12} of the AO deflector 12 is formed into the step-like configuration and the slow driving signal S_{30} of the piezo device is formed into the linear configuration.

FIG. 9 is a diagram for illustrating the positions of the fluorescent light spot images formed by these two signals on the fluorescent light detection plane Σ_{PH} . The change from the above to the below in this drawing represents the lapse of a time t . Two graphs on the left side indicate the changes of S_{B12} and S_{30} . Although the number of the steps is equal to 10 in FIG. 8, it is equal to 5 in this drawing. Solid-line circles 3211', 3221', 3231', ... that exist on the right side of the graph in FIG. 9 indicate the position shift of the fluorescent light detection multi-spot image in the case where, as was explained in FIGS. 6A to 6E, the position correction by the piezo device has not been performed yet. Incidentally, the right direction (transverse direction) in the drawing represents the arrangement direction x_A of the spot array, and solid-line circles 3212', 3222', 3232', ... indicate the position shift of the fluorescent light spot image adjacent to the above-described image. Moreover, dotted-line circles indicate the consequences obtained as the result of executing the position correction by the piezo device.

09070652 100400

Namely, even when the AO deflector 12 had finished performing the step displacement of the excitation light and thus the excitation light has already stopped, the piezo device is still driving the deflection linearly. As a result, the corrected position of the fluorescent light spot image formed on the fluorescent light detection plane Σ_{PH} is displaced as is indicated by 3211₋, 3211, 3211₊ by a slight amount though, while the excitation light continues to stop (The corrected position of the adjacent fluorescent light spot image is displaced as is indicated by 3212₋, 3212, 3212₊ by a slight amount, though).

When the excitation light has been step-displaced to the next irradiation position on the DNA chip, and even if it continues to stop there, the corrected position of the fluorescent light spot image is displaced as is indicated by 3221₋, 3221, 3221₊ by a slight amount, though (The corrected position of the adjacent fluorescent light spot image is displaced as is indicated by 3222₋, 3222, 3222₊ by just a slight amount, though). In order to cover and detect this slight amount of displacement of the fluorescent light spot images, as illustrated in FIG. 10, there is provided an arrangement of ellipse-shaped apertures 3201, 3202,, 320M on a fluorescent light detection light-receiving plane (or, a plane conjugated with the light-receiving plane) 320, the longer radius of the ellipse being in the spot array direction x_A . In the

09678652.100400

case of the above-described detection using the fiber, it is all right to set a condition that the fiber light-receiving end plane should include the ellipse.

FIG. 11 is a diagram for illustrating an embodiment in the present invention. The same reference numeral as that in FIG. 1 denotes the same component or the same function. In the present drawing, there is illustrated only a portion relating to the generation of the multi-spot excitation lights out of the entire apparatus in FIG. 1. The configuration components other than the portion are basically the same as those in FIG. 1. A reference numeral 14' denotes a multi-spot generating hologram.

FIG. 12 is a diagram for illustrating a method of creating the multi-spot generating hologram. As illustrated in FIG. 12, a laser light is irradiated with a mask 18 having pinhole array $1j_11'$, $1j_12'$,, $1j_1M'$ apertures having hole diameters corresponding to dimensions of the multi-spot excitation lights. Then, the transmittance lights having passed through the mask are converged onto a hologram storage medium by a Fourier transformation lens 15. Next, the converged position is irradiated with a reference light 1000 from a somewhat oblique direction at an incident angle $\phi = \phi_0$ in a superimposed manner, thereby forming the Fourier transformation hologram at the above-described converged position.

In order to enhance the light utilization

5

The hologram created in this way is used in the multi-spot excitation lights-generating system in the DNA inspecting apparatus in FIG. 11.

15

20

25

$1j_1, 1j_2, \dots, 1j_M$, a spot array that is the same as the pinhole array at the time of creating the hologram in FIG. 12.

Next, changing the frequency of the AO deflector brings about a slight amount of change in the incident angle into the hologram, thereby bringing about a slight amount of change in the angles of the multi-spot reproduced lights as well. As a result, it turns out that a position equivalent to the adjacent pixel is illuminated and excited. Accordingly, a sequential driving of the AO deflector makes it possible to execute the multi-spot excitation illumination of the DNA chip in the step-like manner, i.e., in such a manner that the position to be irradiated is changed in sequence on the one-pixel pitch basis.

FIG. 13 is a diagram for illustrating another embodiment of the DNA inspecting apparatus in the present invention. The same reference numeral as that in FIG. 1 denotes the same component. In the present embodiment, unlike the embodiment in FIG. 1, the detection in a 2-dimensional manner is executed as well simultaneously. Namely, the excitation illumination light is caused to pass through an illuminating lens 13' capable of simultaneously illuminating a 2-dimensionally-broad range. Moreover, the excitation illumination light is reflected by a wavelength selection beam splitter 30', then illuminating a 2-dimensional microlens array 14'. The 2-dimensional

microlens array 14' has the same functions as those in the case where the 1-dimensional microlens array has been already explained using FIGS. 1 to 4, and what differs therefrom is the 2-dimensional array arrangement alone. Consequently, as illustrated in FIG. 14, 2-dimensional microscopic spots 1410' are formed at focal point positions of microlenses 141'.

In the case of the present embodiment, pinhole apertures are bored with the positions of 1410' as their center. In this way, the DNA chip is irradiated with only the lights that have passed through the pinhole apertures. A ratio between a diameter d of the microscopic multi spots and an arrangement pitch p of the spots is equal to an integer that is larger than 2 and that, preferably, is larger than 5. As illustrated in FIG. 13, a high-resolution lens 16' causes the DNA chip to be simultaneously irradiated and excited with the 2-dimensional multi-spot lights having passed through the pinhole apertures. The pixels undergoing the excitation irradiation, i.e., $2x11y11$, $2x12y11$, $2x11y21$, $2x21y11$, ... have an equal pitch spacing with 4 pixels skipped.

Fluorescent lights generated from the above-described pixels that have simultaneously undergone the excitation irradiation pass through the above-described high-resolution lens 16', then passing through the respective pinholes 1410' on the lower surface of the microlens array. The fluorescent lights having passed

through the pinholes pass through the respective micro-
lenses, thereby being enlarged up to a size of the
upper surfaces (convex surfaces) of the microlenses.
The fluorescent light intensities on the upper surfaces
5 of the microlenses are image-formed onto a high-
sensitivity image storage type 2-dimensional sensor 32'
through the wavelength selection beam splitter 30' and
an image-forming lens 31'. Although the interference
filter is not illustrated in the present drawing, the
10 interference filter, or the color filter that permits a
wavelength longer than the fluorescent lights to pass
through is provided between the wavelength separating
beam splitter 30' and the 2-dimensional sensor 32'.

In the 1-dimensional and 2-dimensional
15 microlens arrays illustrated in FIG. 4 and FIG. 14,
respectively, a light incoming into an intermediate
area between the adjacent microlenses in the respective
microlenses is in a danger of becoming a scattered
light and then a noise light. Thus, by performing a
20 masking (not illustrated) by which the intermediate
area is covered with a light-shielding portion composed
of a material such as chromium oxide, it becomes
possible to eliminate such a noise.

FIG. 15 and FIG. 16 illustrate a spectro-
25 scopic reflection characteristic and a spectroscopic
transmittance characteristic respectively of the wave-
length separating beam splitters 30, 30' and the
interference filter 34, which have been used in the

004001 2592960

above-described embodiments and in FIGS. 1, 5, 7, and 13. The use of both of the apparatuses makes it possible to decrease the influences of the excitation lights, thereby allowing the precise detection to be executed. In the drawing, λ denotes a wavelength of the excitation lights. The excitation wavelength bandwidth is narrow because the laser light is usually used in order to increase a per-unit area intensity of the spot irradiation. λ_L denotes a central wavelength of the fluorescent lights to be detected.

As the fluorescent material added to the DNA fragment to be hybridized, several types of fluorescent substances are employed. For example, when employing often employed Cy5 (Cyanine5), an absorption peak wavelength of the fluorescent material is equal to 649 nm and a peak wavelength of the fluorescent lights is equal to 670 nm. Also, on an even shorter wavelength side, when employing Cy3 (Cyanine3), the absorption peak wavelength of the fluorescent material is equal to 550 nm and the peak wavelength of the fluorescent lights is equal to 570 nm. Since the spectroscopic absorption characteristic of the absorbing material has a bandwidth, it is not always required to cause the wavelength of the excitation laser light to coincide with the absorption peak wavelength. Accordingly, there is used a laser light the wavelength of which is close to the absorption peak wavelength.

In the case of Cy5, there is used a red He-Ne

09678652 100400

laser light at the wavelength of 633 nm or a semicon-
ductor laser light at the wavelength of 635 nm. In the
case of Cy3, there is used a green He-Ne laser light at
the wavelength of 544 nm or the like. In the inter-
5 ference filter and the wavelength separating beam
splitter for extracting only the fluorescent lights, as
the central wavelength, a wavelength is selected which
is close to the fluorescent light peak wavelength and
at which it is easy to separate the excitation lights.

10 In the above-described fluorescent light
detection, it becomes of the utmost importance to
completely light-shield the excitation lights especial-
ly when the fluorescent lights are weak.

FIG. 17 is an embodiment-illustrating diagram
15 in the present invention, where it is intended to
execute the above-described light-shielding of the
excitation light more completely. Namely, the light-
shielding based on the present embodiment is executed
in the following cases: The use of the interference
20 filter or the wavelength separating beam splitter alone
is insufficient for the light-shielding, or it is
desirable to increase the band half-value width of the
interference filter in order to increase the fluo-
rescent light detection intensities. In FIG. 17, the
25 same reference numeral as that in FIG. 1 have the same
component or the same function.

A multi-spot array 111,, 11M formed on a
plane Σ_f by the microlens array or the hologram is

004001 2597950

image-formed onto the DNA chip as excitation lights through the operation of the lens 15 and the objective lens 16. At this time, the respective multi-spot lights pass through a center of an incident pupil EP_0 of the objective lens with a spread the radius of which is substantially RNA_{σ} . Setting a numerical aperture and the focal length of the objective lens to be NA and f, respectively, a spot diameter D_s of the excitation lights on the DNA chip is given by the following equation:

$$D_s = 2k_1 f \lambda / RNA_{\sigma}' \quad (\text{where } k_1 = 0.6)$$

Representing, by p, a pixel resolution (the pixel pitch) for the DNA chip detection, this value is substantially equal to D_s . Assuming that p is equal to $2 \mu\text{m}$ and the excitation light wavelength λ is equal to 633 nm, a value RNA_{σ}'/f becomes equal to 0.19. The value RNA_{σ}'/f is a NA of an illumination for illuminating the spot of $2 \mu\text{m}$ (i.e., a minimum NA of the objective lens needed in order to image-form the $2 \mu\text{m}$ spot). Representing this value by NA' , the NA' is given as follows:

$$NA' = \sin(\tan^{-1} (RNA_{\sigma}' / f)) \doteq RNA_{\sigma}' / f = 0.19$$

In order to detect the weak fluorescent lights, the NA of the objective lens 16 falls in the range of 0.7 to

0.9.

Next, the respective excitation spot lights, which have passed through the incident pupil of the objective lens with the above-described spot diameter, irradiate the DNA chip with the excitation spot lights of about 2 μm through the operation of the objective lens. Since the objective lens is both-telecentric in nature, about 4 to 8% of the excitation lights out of the excitation lights incoming into the DNA chip in perpendicular thereto are regularly reflected by the chip surface, then returning back to the objective lens. The wavelength separating beam splitter permits most of the regularly reflected excitation lights to pass through, but the beam splitter reflects the regularly reflected excitation lights by just a slight amount. Then, the slight amount of reflected excitation lights travel toward the fluorescent light detecting system 3.

The fluorescent light detecting system 3 includes the interference filter 34, thereby light-shielding the excitation lights. Nevertheless, the complete light-shielding is a difficult task. Namely, trying to widen the bandwidth of the interference filter so as to detect the fluorescent lights as much as possible results in just a slight amount of leakage of the excitation lights. Thus, a lens system 31' for image-forming and detecting the fluorescent spot lights onto a fluorescent light detection plane (or, a plane

conjugated therewith) is configured with lens systems 311, 312 as illustrated in the drawing. This configuration is designed so as to image-form the objective lens pupil at a position existing between 311 and 312.

5 A space filter 35 is located at this position conjugated with the pupil. The space filter 35 has a configuration as illustrated in FIG. 18.

The light-forming magnification of the objective lens pupil' surface toward the space filter 35 by the lens system 311 is assumed to be 1 time. The space filter has a circle-shaped light-shielding portion 351 of a radius RNA_{σ} in the central portion of an aperture, the aperture having a radius RNA that is equal to a radius of the objective lens pupil from the optical axis center of a light-shielding portion 353.

15 The multi-spot excitation lights, which had been regularly reflected by the DNA chip, turns out to have the beam radius of RNA_{σ} on the space filter. Consequently, if $RNA_{\sigma} > RNA_{\sigma}'$ holds, the regularly reflected excitation lights are light-shielded by the light-shielding portion 351.

20

Meanwhile, the fluorescent lights excited and generated by the multi-spot excitation lights are launched into the objective lens with almost no directivity, then incoming into the space filter. The light-shielding portion 351 light-shields the fluorescent lights as well, but a ratio of the light-shielded fluorescent lights toward the space filter

25

09678666 100400

incoming fluorescent lights becomes equal to $(NA'/NA)^2$. Substituting the above-described value, this value is found to be 7 (when $NA = 0.7$) to 4 (when $NA = 0.9$) %, which is a loss of a negligible order.

- 5 In this way, it is possible to reduce the unnecessary excitation lights tremendously without lowering the light amount of the fluorescent lights to be detected. The fluorescent light detection lights having passed through the space filter pass through the
- 10 lens 34 and the interference filter 34, then image-forming the spot images on the DNA chip onto the detection plane, i.e., the optical fiber light-emitting ends, so as to be subjected to the fluorescent light detection.
- 15 FIG. 19 is an embodiment-illustrating diagram in the present invention, which indicates a method of preventing the excitation lights from being guided into a fluorescent light detecting optical path. The same reference numeral as that in FIG. 1 denotes the same
- 20 component. In the present embodiment, a polarization beam splitter 30" is employed as a beam splitter for branching off the fluorescent light detecting optical path from an excitation light optical path. Namely, a split surface of the polarization beam splitter is
- 25 irradiated with the excitation lights that are P-polarized toward the split surface. Then, since the excitation lights having been reflected on the DNA chip surface and having returned back still remain P-

09678652 100400

09678652 100400

polarized, the excitation lights pass through the polarization beam splitter and never enter the fluorescent light detecting optical path. On the other hand, since the polarization state of the generated fluorescent lights differs from that of the excitation lights, the S-polarized fluorescent lights are reflected by the polarization beam splitter 30", then being guided into the fluorescent light detecting optical path. In this way, this method makes it possible to prevent the excitation lights from being guided into the fluorescent light detecting optical path.

FIG. 20 is an embodiment-illustrating diagram in the present invention, where the fluorescent light detection is executed using the optical fibers and the multi-channel photomultiplier tube. Namely, FIG. 20 illustrates the concrete content of the detection of the fluorescent light multi-spot images in the embodiments illustrated in FIGS. 1, 5, 7, 17, and 19. As illustrated in FIG. 21, the light-receiving end of the fiber system 32 for the fluorescent light multi-spot images the multi-spot number of which is M or more is the multi-lens array 321 including 1-dimensionally arranged M lenses.

As having been explained in FIG. 7, using the respective microlenses, the fluorescent light multi-spot images are launched into the cores through which a light passes in the fibers. If, as illustrated in FIG.

In the case of the embodiment in FIG. 21, a 2-dimensional lens array 3241 is provided at the light-emitting ends of the fibers in the corresponding manner. The fluorescent lights emitted from the
15 respective fibers pass through the respective lenses, thereby being directly converged onto 2-dimensional light-receiving apertures (photoelectric plane) 3311 of the multi-channel photomultiplier tube. In the embodiments illustrated in FIGS. 20, 21, the 2-dimensional
20 multi-channel photomultiplier tube is employed. When using the 1-dimensional multi-channel photomultiplier tube as well, configuring the light-emitting ends to be 1-dimensionally arranged also allows the detection to be executed by the same method.

25 FIG. 22 is an embodiment-illustrating diagram
in the present invention. In the present embodiment,
as the excitation lights, there are used excitation
lights having a plurality of different wavelengths.

When the fluorescent lights to be detected are of different types, the entire light-source system

When the fluorescent lights to be detected are of different types, the entire light-source system

FIG. 26 is another embodiment-illustrating diagram, where the above-described plurality of types of fluorescent lights are used. Unlike the case in FIG. 22, irradiations with the plurality of types of excitation lights are performed simultaneously, thereby trying to shorten the detecting time. In FIG. 26, excitation lights, which are emitted from light-source systems 11A', 11B', and 11 C' with a plurality of different wavelengths λ_A' , λ_B' , and λ_C' corresponding to, for example, 3 colors of red, green, and blue, are synthesized effectively into one optical path by wavelength selection synthesizing mirrors 51, 52. Namely, the wavelength selection synthesizing mirror 51 permits blue to pass through and causes green to be reflected. Also, the wavelength selection synthesizing mirror 52 permits red to pass through and causes green and blue to be reflected.

FIG. 26 is another embodiment-illustrating diagram, where the above-described plurality of types of fluorescent lights are used. Unlike the case in FIG. 22, irradiations with the plurality of types of excitation lights are performed simultaneously, thereby trying to shorten the detecting time. In FIG. 26, excitation lights, which are emitted from light-source systems 11A', 11B', and 11 C' with a plurality of different wavelengths λ_A' , λ_B' , and λ_C' corresponding to, for example, 3 colors of red, green, and blue, are synthesized effectively into one optical path by wavelength selection synthesizing mirrors 51, 52. Namely, the wavelength selection synthesizing mirror 51 permits blue to pass through and causes green to be reflected. Also, the wavelength selection synthesizing mirror 52 permits red to pass through and causes green and blue to be reflected.

00400T" 25387950

The synthesized 3 colors pass through a beam splitter 30' and, after passing through the lens 15, the deflection mirror 300, and the objective lens 16, perform 3-color simultaneous spot excitation illuminations with the 3 colors onto the DNA chip. The respective fluorescent materials are excited at each wavelength and emit lights with the respective fluorescent colors. The fluorescent lights emitted have wavelengths that are slightly longer than those of the excitation lights. This condition makes it possible to separate, using wavelength separating beam splitters 53, 54, the wavelengths of the 3-wavelength fluorescent lights excited by the 3-wavelength excitation lights. Namely, the wavelength separating beam splitter 53 causes the blue fluorescent light to be reflected and permits the green and the red to pass through. Also, the wavelength separating beam splitter 54 causes the green to be reflected and permits the red to pass through.

20 In optical paths resulting from the separation into the respective 3 colors in this way, there are located interference filters 34C, 34B and the filter 34A that each permit the respective fluorescent lights alone to pass through with a high-purity. Then, 25 the microscopic spot images of the respective fluorescent lights are detected simultaneously by the above-described method using multi-channel photomultiplier tubes 33C', 33B', and 33A' through fibers.

In the embodiments in FIGS. 22, 26, the deflection mirror 300 performs the array direction scanning of the excitation multi-spot lights. As the deflection mirror, there is employed a mirror of the piezo driving system or of the galvanometer mirror type. In this case, unlike the embodiment explained in FIG. 1, the multi spots are subjected not to the step displacement but to a continuous (linear) scanning. The multi spots on the DNA chip are scanned, but one and the same (identical) deflection mirror is used in the detecting optical path as well. As a result, unmoved multi spots are image-formed at the ends of the fluorescent light detecting fibers. On account of this, it turns out that pixel addresses are determined based on the deflection angle of the deflection mirror.

Based on the relationship between the pixel addresses and the deflection angle, a plurality of fluorescent light detection signals obtained from the multi-channel photomultiplier tubes in a parallel manner are organized and stored by the control apparatuses 4' (FIG. 22) or 4" (FIG. 26). Such data processing, of course, requires that the measuring and detecting conditions be inputted in advance. These pieces of input information are inputted from a terminal 41' or from a high-order computer 40 then, as necessary, data on the measured and inspected result is transferred to the computer.

In the embodiment in FIG. 26, the explanation

00400T 2594950

has been given concerning the case where the irradiations with the plurality of excitation lights having the different wavelengths are performed simultaneously. By the way, in the case where there exist an overlap
5 between the wavelength bands of the plurality of excitation lights and those of the fluorescent lights at which the respective excitation lights aim, a shutter situated near the light-sources and not illustrated is used toward the overlapped excitation
10 light or the fluorescent light detection is executed with the time shifted by an ON-OFF of the light-sources themselves.

FIG. 23 is an embodiment-illustrating diagram in the present invention, where a plurality of semiconductor lasers 111A2, 111A2, ... having substantially
15 the same wavelength are employed as the excitation light light-source. The semiconductor laser is of a small volume, producing a comparatively high-output, and is inexpensive. As a consequence, as illustrated
20 in the drawing, configuring a multi-spot light-source using a large number of semiconductor lasers makes it possible to irradiate the DNA chip with intense multi-spot excitation lights, thereby allowing the high-speed detection to be implemented. The lights emitted from
25 the respective semiconductor lasers are taken into light-receiving ends of fibers 120A1, 120A2, ... by lenses 112A1, 112A2, ...

The laser lights emitted from the light-

00400T 25982960

emitting ends, as illustrated in FIG. 24, are converged onto a pinhole arrangement 111, 112, ... through a microlens array. Then, the transmittance lights having passed through the pinhole arrangement are used as the multi-spot excitation lights.

If the semiconductor lasers are not usable as the excitation lights, there are used high-output solid-state lasers excited with the semiconductor lasers, and high-output gaseous lasers. In such laser light-sources, by using an emitted beam in such a manner as to be split by a method illustrated in FIG. 25, it becomes possible to form multi-spot excitation lights having substantially the same intensity and substantially the same beam configuration.

Namely, the beam emitted from a laser light-source 111A' is split using multi-splitting beam splitters 1110A', 1120A', ... It is assumed that the number of the splitting is equal to k and reflectances of beam-split lights from the 1st stage of the splitting through the 2nd stage, the 3rd stage, ... to the k -th stage are equal to $r_1, r_2, \dots r_j, \dots r_k$. Considering that r_k is equal to 1 and since the respective beam-split lights are equal in their intensities, with reference to an arbitrary j ($1 \leq j \leq k$),

$$r_j = 1 / (k - j + 1)$$

should be satisfied in order to form the above-

described multi-spot excitation lights. Namely, at 1110A', since k is equal to 4, i.e., 4-splitting, r_1 , r_2 , r_3 , and r_4 become equal to $1/4$, $1/3$, $1/2$, and 1, respectively. Similarly, since 3-splitting is performed at 1120A', r_1 , r_2 , and r_3 become equal to $1/3$, $1/2$, and 1, respectively. In this way, the laser lights having the same intensity and the same beam configuration are launched into a lens array 112A1', then being launched into cores of the fibers.

10 In the embodiment in FIG. 23, the plurality of semiconductor lasers are employed as the excitation light light-source for the generation of the multi-beam spots. In the case where the available laser light power is inadequate, however, it becomes required to form the multi-spot excitation lights with the use of a plurality of gaseous lasers other than the semiconductor lasers or a plurality of lasers based on the 2nd harmonics. In such a case, the systems illustrated in FIG. 25 are used in plural number and the fiber light-emitting ends picked up from the plurality of systems are arranged on a 1-dimensional line or a 2-dimensional plane. This makes it possible to obtain the multi-spot excitation lights with a high-excitation intensity.

In the above-described case where the plurality of excitation lights are used, depending on the excitation wavelength, there arises a necessity of using various types of different lasers, such as the semiconductor laser, the gaseous laser, and the solid-

state laser using the 2nd harmonics excited with the semiconductor. In such a case, it is all right to form the multi-spot excitation lights in accordance with the above-described method illustrated in FIG. 23 or FIG.

5 25.

FIGS. 27, 28 are embodiment-illustrating diagrams in the present invention. In the drawings, by eliminating the influences of the fluorescent lights and the scattered lights generated by the excitation multi-spot lights from a foreign substance mixed in the DNA chip, or the influence of a scattered light from a foreign substance in the fluorescent light detecting optical system, it is made possible to implement the high-accuracy fluorescent light detection. A reference numeral 11' denotes an excitation light-source, which causes a light to pass through a pinhole aperture array 14' through a fiber so as to create the excitation multi-spot lights. The multi-spot lights are image-formed onto the DNA chip through the operation of the lens 15 and the objective lens 16. A space filter 161 is located at the position of an incident pupil of the objective lens.

The excitation multi-spot lights are set so that the multi-spot lights pass through a position 163 (refer to FIG. 28) shifted off from a center of the incident pupil. Namely, as illustrated in FIGS. 29, 30, the respective multi-spot lights pass through a portion shifted off from an optical axis of the

09678652 100400

Also, the excitation lights reflected
10 regularly by the DNA chip pass through the objective
lens, then passing through a position (the position
indicated by 162 in the drawing) that is symmetrical
with 163 with the lens' optical axis as the symmetrical
center on the pupil 161 (refer to FIG. 28).

15 Thus, as illustrated in FIG. 28, forming, in
this position, a member 162 for light-shielding the
regularly reflected excitation lights allows the
regularly reflected excitation lights to be light-
shielded by this member 162. In this way, the position
20 off from the center of the pupil is set to be the
optical path of a primary light-ray of the excitation
lights. Moreover, with reference to the incident angle
 θ_i of this primary light-ray, a condition $\theta_i > \theta_{I/2}$
is made to be satisfied. This condition makes it
25 possible to light-shield the regularly reflected
excitation lights on the pupil without light-shielding
the excitation lights on the pupil. It is needless to
say that the present embodiment has the effect of

In the embodiment in FIG. 27, in addition to this effect, the influences of the foreign substance mixed on or in the DNA chip are eliminated in the following way: Namely, if there exists the foreign substance such as various kinds of proteins mixed at the time of forming the DNA sample, the irradiation of the foreign substance with the excitation lights causes the excitation lights to be scattered, because the dimension of such a foreign substance is small, i.e., several μm . Also, in the case of the above-described foreign substance of the organic substance type, intense fluorescent lights are emitted from the foreign substance, becoming the fluorescent lights that are more intense than the fluorescent material added to the DNA to be detected.

As illustrated in FIG. 30, the scattered
excitation lights pass through a dotted-line surrounded
20 area $L + S$ determined by the NA ($= \sin \theta_{L+S}$) of the
objective lens. Then, after passing through the
objective lens, the scattered excitation lights pass
through a portion other than the light-shielding member
162 of the space filter, leaking into the fluorescent
25 light detecting system. Only this leakage of the
scattered excitation lights is extracted using a wave-
length separating beam splitter 61, then executing the
image detection. The wavelength separating beam

splitter permits the fluorescent lights to pass through and causes the excitation lights to be reflected. Although, in FIG. 29, the wavelength separating beam splitter 61 is inserted in optical paths behind the wavelength separating beam splitter 30", it may be inserted in optical paths before the beam splitter 30". In this way, in much the same manner that the fluorescent light image is photographed by a detector 33' such as the multi-channel photomultiplier tube, an excitation light scattered image S100 ((refer to FIG. 29) of the excitation lights scattered by the foreign substance is detected as an image by a detector 62.

FIGS. 31A, 31B indicate, at a signal level on the per-pixel basis, a fluorescent light image signal D_L and an excitation light image signal D_S that have been detected in this way. Namely, numerals 1, 2,, 25 denote detected pixel addresses and numerals (1), (2), (3), (4), (5) denote addresses of cells to which the same DNA sequence is hybridized. Namely, for example, the pixels at the addresses 1, 2, 3, 4, 5 belong to the cell (1). Although, actually, the pixels in the cells are 2-dimensionally located and there exist, for example, 5×5 pixels, the pixels are 1-dimensionally located in order to make the drawings-accompanying explanation easy to understand. If the detection is exerted upon a pixel where the foreign substance exists, the scattered excitation light from the pixel exceeds a threshold value D_{ST} .

In FIG. 31B, at the pixel addresses 9, 10, 11, 12, and 16, 17, 18, 19, 20, the excitation light image signal D_s exceeds the threshold value D_{st} . Consequently, the information on the fluorescent light image signal D_L existing at the corresponding addresses is strongly influenced by the foreign substance. Accordingly, an average value of the fluorescent lights in each cell is determined by discarding the information at these addresses. Namely, concerning the cell (2), the average value is determined not by using the information at the addresses 9, 10 but by using only the information at the remaining addresses 6, 7, 8. Similarly, concerning the cell (3), the average value is determined by using only the information at the addresses 13, 14, 15. In the cell (4), the scattering from the foreign substance occurs in all the pixels, and thus this cell is regarded as being invalid. The average intensity in each cell is determined in this way as is illustrated below in the graph in FIG. 31C. This allows the influences of the foreign substance to be reduced tremendously, thereby making it possible to execute the precise fluorescent light detection.

Incidentally, in the optical systems of the embodiments explained using FIGS. 27 to 30 where the influences of the foreign substance are eliminated, there are provided the optical systems where the excitation lights illuminate the DNA chip after passing through the objective lens. However, the configuration

00400T 25382960

is also allowable where the irradiation with the
excitation lights is performed from between the objec-
tive lens and the DNA chip in an oblique direction
without passing through the objective lens. In this
5 case, since the regularly reflected excitation lights
are not launched into the objective lens, a space
filter (which is equivalent to 161) becomes unneces-
sary.

FIG. 32 is an embodiment-illustrating diagram
10 in the present invention. The reference numerals
denote the following components: 1 the multi-spot
excitation lights-irradiating system the detailed
embodiments of which have been explained already, 3
the fluorescent light detecting system for detecting
15 the fluorescent lights generated by the multi-spot
excitation lights, the details of which have been also
explained already. The fluorescent material attached
to the DNA hybridized onto the DNA chip 2 is irradiated
with the microscopic multi-spot excitation lights of
20 several μm through the use of the objective lens 16.
In order to accomplish this, it is required to always
maintain the distance between the objective lens and
the fluorescent light plane at a fixed spacing within
the focal depth so that the spot size is kept at a
25 constant value. For the purpose of this, there is used
a focal point detecting system 7 that is structurally
integrated with the objective lens 16 for implementing
the rigidity. The focal point detecting system 7

004007 25982950

includes an oblique beam spot irradiating system 71 and a spot position detecting system 72. The oblique beam spot irradiating system 71 irradiates the fluorescent light plane on the DNA chip with the microscopic spots from an oblique direction.

The irradiation with the spots is performed, and the spacing between the objective lens 16 and the fluorescent light plane is detected. Then, the objective lens 16 is controlled so as to be driven in the z direction in accordance with the detection signal by an objective lens up-and-down driving mechanism 73 so that, even if a stage 80 for mounting the DNA chip 2 thereon is driven in x, y directions by a driving motor 83(84), the above-described fixed spacing is maintained. A numeral 82 denotes a length-measuring device of x, y stage.

FIG. 33 illustrates an example of a cross sectional structure of the DNA chip. In this embodiment-illustrating diagram, the fluorescent light plane is a plane Σ_2 . Namely, there exists the fluorescent light plane Σ_2 on a flat substrate 23 such as a glass. Between this plane and a plane Σ_1 on a glass substrate 21, there exists a clearance 22 into which a liquid containing the fluorescent material-added DNA to be inspected is poured for implementing the hybridization. At the stage of the DNA inspection, the clearance is filled with the liquid. However, depending on the cases, the clearance is left empty. Also, in some

cases, the plane Σ_1 is selected as the fluorescent light plane, and the substrate 23 is composed of an opaque substance or a light-absorbing material.

A light beam f_0 irradiation of which is performed from an oblique direction by the oblique beam spot irradiating system 71 so that the light beam is converged onto the fluorescent light plane, is regularly reflected on the following 4 planes: An upper plane Σ_3 and the lower plane Σ_1 of the upper substrate 21, and the upper plane Σ_2 and a lower plane Σ_4 of the lower substrate 23. Light-rays l_3 , l_1 , l_2 , and l_4 , which are formed by the regular reflections of a primary light-ray f_{0m} of the oblique irradiation beam f_0 , are each image-formed by an image-forming lens 721 at positions P_3 , P_1 , P_2 , and P_4 on a plane equivalent to a light-receiving plane of a light-receiving position sensor 722. The position of the fluorescent light plane is determined in advance and accordingly, if the respective planes Σ_3 , Σ_1 , Σ_2 , and Σ_4 are away from each other to a certain extent, the following method makes it possible to execute the height detection of a desired detection plane alone: The dimension of the light-receiving position sensor 722 and the image-forming magnification of the lens 721 are determined beforehand so that only a spot image resulting from the reflected light-ray l_2 from the plane to be detected (which is Σ_2 in this embodiment-illustrating diagram) is received and the other spot images are image-formed

00678652 100400

outside the light-receiving aperture.

Namely, in this embodiment, it becomes possible to capture only the regularly reflected light reflected from the plane Σ_2 and thus to detect the spot position on the position sensor, i.e., the height position of the plane Σ_2 . Then, based on this detected information and in accordance with the control apparatus 4, the objective lens and the focal point detecting system 7 integrated with the objective lens are displaced slightly in an up-and-down direction by the driving mechanism 73. This allows the fluorescent light detection to be executed always in the focus-achieving state.

If the incident angle of the oblique incidence focus detecting light in FIG. 33 is close to Brewster angle, causing the detecting light to be launched in the P-polarized state gives rise to an extremely small reflection on the plane surface, thereby making it difficult to execute the detection. Accordingly, there is employed the S-polarized detecting light. The employment of the S-polarization enhance the reflectance on the plane surface more in comparison with that of the P-polarization no matter what value the incident angle is. This is advantageous enough.

FIG. 34 is an embodiment-illustrating diagram in the present invention, where the focal point detection is executed through the objective lens 16. A

09678652.1004.00

laser light having been guided by a fiber 74 from a near-infrared semiconductor laser light-source not illustrated, after being emitted from the fiber, passes through a beam splitter 76, a lens 77, and a wavelength separating beam splitter 300". Then, the light passes through the objective lens 16 so as to be converged, and the fluorescent light plane on the DNA chip 2 is irradiated with the converged light from oblique directions. The incident angle θ of this irradiating light is equivalent to the numerical aperture NA of the objective lens in its magnitude (an incident angle that is somewhat smaller than $\sin\theta = NA \doteq 0.8$). The regularly reflected light passes through the objective lens again, eventually forming, onto a position sensor 73', an image of the light-converged point on the DNA chip 2. Then, the position sensor 73' detects the position of this image. From this detected position, the height of the plane in the DNA chip can be determined. The objective lens is displaced in the up-and-down direction so that the image is image-formed at a reference point on the position sensor 73'. This, in the same way as the embodiment in FIG. 33, makes it possible to detect the focus position of the fluorescent light plane in the chip. Just like the present embodiment, by employing the light the wavelength of which is longer than that of the detected fluorescent light as the light to be used for the focal point detection, it becomes possible to execute the focal

point detection precisely without exciting the fluorescent material, i.e., without generating the detection noise.

Incidentally, the wavelength separating beam splitter 300" in FIG. 34 permits the near-infrared light to pass through and reflects the excitation light and the fluorescent light used for the fluorescent light detection. The irradiation with a 1-dimensional excitation light spot array formed by a 1-dimensional excitation light irradiating optical system 1 is performed toward the fluorescent light plane in the DNA chip through the lens 15, the wavelength separating beam splitter 300", and the objective lens 16. A fluorescent light detecting optical system 3 detects the fluorescent light generated. The displacement of the excitation light spot array irradiating positions in the array direction is executed by causing the wavelength separating beam splitter 300" to perform the microscopic rotation.

Hereinafter, referring to FIGS. 35 to 40, the explanation will be given concerning a method of executing, all over the entire cells in the DNA chip, the fluorescent light detection toward the DNA chip that has been explained so far using the above-described respective embodiments.

FIG. 35 illustrates the entire structure of the DNA chip. A numeral 204 denotes the whole case for housing the DNA chip. The DNA chip is a glass

09678652 100400

substrate on an inner side of a window 200 formed on this case, and the chip is fixed to the case 204. The fluorescent material-added DNA fragment is hybridized with an area 202 on the inner side of the window. In
5 an area spreading outside the area 202 and inside the window 200, there are described alignment marks 201 for the positioning.

The relative positions between the cell 20 explained in FIG. 2 and the alignment marks 201 are
10 designed and formed with an accuracy of several-tenth μm , the cell 20 including $N \times N$ (in FIG. 5, 5×5) pixels (indicated by the bold line) in which the fragment of the same DNA information is planted (i.e., the probing is performed).

15 The DNA chip is mounted on the detecting apparatus the embodiments of which have been explained already. Then, in an alignment detecting optical system (not illustrated) implemented in the detecting apparatus, using a device such as a mark position
20 detecting 2-dimensional CCD, the positions of at least 2 of the alignment marks 201 are detected as positions on the CCD. Also, the position of the DNA chip at the time of executing this mark detection is detected using, for example as is illustrated in FIG. 32, the
25 length-measuring devices 81, 82 for detecting the position in the x and y directions. The length-measuring devices are provided on a chuck on which the DNA chip is mounted.

0967853-100400

09678653-100400

The spacing between the optical axis of the above-described CCD detecting optical system and the detecting optical axis in the previously-described various types of fluorescent light detecting optical systems is fixed. This condition allows the pixels to be detected at the right positions from the above-described spacing, the above-described alignment mark detected positions by the CCD, and the detected position by the length-measuring devices, the pixels corresponding to more minute division of the inside of each cell on the DNA chip. At this time, if the detection of 2 or more of the alignment mark positions indicates that the DNA chip has been rotated, this rotation is corrected using a rotation mechanism not illustrated. Incidentally, the right position detection after this rotation correction is performed as necessary. Even if this rotation correction is not performed, if the amount of the rotation is small, it is also allowable to detect this rotation amount by the above-described method and to correct the x, y coordinates in accordance with the rotation amount detected. Also, it is possible to correct and detect the above-described multi-spot lights by a microscopic rotation of the optical system.

25 As having been explained so far, the detection of the alignment marks and the length-measurement of the DNA chuck make it possible to detect the pixels in each cell on the DNA chip with the precise position-

ing accuracy. As a consequence, in accordance with the following method, it becomes possible to execute the fluorescent light detection toward all the pixels in the chip in sequence, at a high speed, and without missing. A reference numeral 2A in FIG. 35 indicates an area detected by one scanning of the chuck. Here, the one scanning of the chuck is executed as follows: An operation of performing the irradiation with the M multi-spot array excitation lights, of performing the sequential scanning by the amount of N pixels in the spot array direction, and of returning the spot array back to an original operational position is repeated, and at the same time, the chuck is scanned in the y direction. Namely, as illustrated in FIG. 36, first, the pixels 2A101, 2A102,, 2A10M on the DNA chip are illuminated and excited simultaneously. Next, the multi spots are displaced by the amount of one pixel-pitch ΔP by the above-described method, and this is continued in sequence.

When, in this way, the displacement by the amount of $N(k)$ pixels is over, it turns out that the detection has been performed by the amount of $MN(k)$ pixels in total, i.e., over a width of $NM\Delta P$, in a 1-dimensional array-like configuration. When the scanning by the amount of $N(k)$ pixels has been finished, the multi-spot array is returned back to the original position. During this, the DNA chip has been displaced by the amount of one pixel in the y direction, which

corresponds to a time-period from a time t_0 to t_1 of y_{st} in FIG. 39. Consequently, during the time-period from the time t_0 to t_1 , the repetition of the above-described operation by the number of the y direction pixels
5 allows the fluorescent light detection to be finished toward all the pixels in the area 2A.

In the case where the above-described operation is performed by the DNA detecting apparatus of the embodiment in FIG. 1, the driving signal of the
10 multi-spot excitation lights by the AO deflector, or the displaced position of the spots is changed as is indicated by S_{px} in FIG. 38. When seen in more detail, the driving signal or the displaced position is step-displaced just like S_{B12} in FIG. 8. Also, the deflection
15 signal of the wavelength selection beam splitter is changed similarly to S_{px} in FIG. 38. The repetition of such changes from the time t_0 to t_1 permits all the area of the area 2A to be detected.

When the detection has been performed to the
20 end at the bottom of the area 2A (the time t_1), as is indicated by x_{st} in FIG. 40, the DNA chip chuck is step-displaced over the width of $NM\Delta P$ in the x direction. After the step displacement, as is indicated by y_{st} after the time t_1 in FIG. 39, the chuck is scanned in an
25 opposite orientation in the y direction. Simultaneously with this, just like S_{px} after the time t_1 in FIG. 38, the deflection signal of the AO deflector 12 and that of the wavelength selection deflecting beam

09678653 100400

Next, the explanation will be given below concerning a time needed to detect all the pixels on the DNA chip. Representing the cell number in the chip by L , each cell is divided into the $N \times N$ pixels so as to avoid the influences of the foreign substance and the like. This makes the total detection pixel number in the chip equal to LN^2 . Setting the simultaneous irradiation spot number of the multi-spot excitation lights and a time needed for the detection with the multi spots to be M and Δt , respectively, and ignoring a time for the spot displacement and a time for the chuck movement in the x direction since these times can be assumed to be shorter as compared with the fluorescent light detecting time, the total fluorescent light detecting time T is given by the following equation:

Next, the explanation will be given below concerning a time needed to detect all the pixels on the DNA chip. Representing the cell number in the chip by L , each cell is divided into the $N \times N$ pixels so as to avoid the influences of the foreign substance and the like. This makes the total detection pixel number in the chip equal to LN^2 . Setting the simultaneous irradiation spot number of the multi-spot excitation lights and a time needed for the detection with the multi spots to be M and Δt , respectively, and ignoring a time for the spot displacement and a time for the chuck movement in the x direction since these times can be assumed to be shorter as compared with the fluorescent light detecting time, the total fluorescent light detecting time T is given by the following equation:

$$\begin{aligned} T &= LN^2 \Delta t / M \\ &= LN^2 / (M/\Delta t) \end{aligned}$$

With reference to the number k of the scannings with the multi spots, a response time T_p of the wavelength separating beam splitter 30 needs to be $k\Delta t$ or larger. Also, the light-source power needs to be $\beta M/\Delta t$ or larger. Also, it is desirable that the spacing between the excitation multi-spot lights be equal to 5 or more in view of the signal-to-noise ratio.

10 At a longer fluorescent light wavelength of 670 nm, the quantum efficiency of the photomultiplier tube used for the fluorescent light detection becomes considerably small, i.e., 5 to 10%. Also, there exists a limit to the output of the laser light used for the
15 excitation. Taking such conditions into consideration and in order to execute the detection as fast as possible, letting, for example, $k (= N) = 10$, $M = 50$, $\Delta t = 50 \mu s$, the cell number $L = 1000 \times 1000$, and the in-cell division pixel number $N = 5$, T becomes equal to
20 25s. Namely, this result satisfies the condition of the fluorescent light detecting time that is smaller than $LN^2 / (6 \times 10^5) \text{ sec}$. Additionally, substituting the above-described values of L and N into this condition, the result is found to be 42 sec. This value satisfies
25 the condition of executing the detection within 1 minute, including attachment/detachment of a sample chip for the use other than the fluorescent light

09678693 100400

detection, inputting of the inspection conditions, and outputting of the result.

Allowing the detection to be executed in 1 minute exhibits an outstanding effect in the case where a lot of specimens to be detected are inspected. For example, 1 minute becomes sufficient to execute an inspection that has necessitated 5 minutes conventionally. Accordingly, even if a preprocessing spends somewhat a longer time, when the number of the specimens becomes around 100, it becomes usually possible to execute the preprocessing in parallel to the inspections of the large number of specimens. This makes it possible to shorten the detecting time by 5 or 6 hours.

The reasons why the present invention permits such a high-speed and high-accuracy detection to be implemented are as follows: The multi spots are used as the excitation lights simultaneously. Moreover, in the fluorescent light detection by each multi-spot excitation light, the detection is executed in a state of enlarging the spot spacing enough so that the influences of the other excitation spot lights can be suppressed up to the smallest possible degree.

FIGS. 41A, 41B, 41C, and 41D are diagrams for illustrating an embodiment of the method and units for obtaining the multi-spot lights according to the present invention.

Using a method described later, substantially

09678652 100400

parallel laser beams emitted from one light-source or a plurality of light-sources are formed into a plurality of (in the drawing, an even number) $N/2$ laser beams that are parallel to each other with a pitch of several mm and that travel in the same direction, then being formed into N laser beams (N is an integer) by $N/2$ beam-doubling prisms 411, 412 and so on. As illustrated in an enlarged perspective view in FIG. 48B, the beam-doubling prism has a cross section of a triangle and a cross section of a parallelogram. Here, the triangle has an oblique side forming an angle of substantially 45 degrees toward the light-emitting surface, and the parallelogram is in contact with this oblique plane and has a total reflection plane that is parallel to this oblique plane.

A light launched into the one side of the parallelogram is reflected on a beam split plane of the triangle' oblique plane by the amount of substantially 50%, and the remaining substantially 50% passes through the beam split plane. The light having passed through the beam split plane passes through the prism of the triangle without being subjected to any change. Meanwhile, the reflected light undergoes a total reflection on the other plane of the parallelogram, then passing through the prism of the parallelogram. In this way, the light having passed through the triangle prism and the light having passed through the parallelogram prism are parallel to each other and have substantially the

09678652 100400

same intensity. Also, the spacing between both of the lights becomes equal to P . As a result, the beam spacing between the adjacent multi beams has become equal to P , which is one-half of the beam spacing $2P$ of the laser beams 81e.

In this way, by a beam-doubling prism array 4e where such beam-doubling prisms are arranged by the number of $N/2$ with the pitch of $2P$, the laser beams 81e are formed into the plurality of N laser beams 8e which travel in substantially the same direction with the pitch of P and the adjacent beams of which are proximate to each other. The plurality of N laser beams 8e, by being launched into a polarization component 11e described later, are formed into a plurality of $2N$ laser beams which travel in substantially the same direction and the adjacent beams of which are proximate to each other.

As illustrated in FIG. 42, the polarization component 11e includes the 1st multi-spot light-doubling prism that has a polarization beam split plane 110e and transparent prisms 111e, 112e. Here, the transparent prisms each have total reflection planes 1101, 1102 that are parallel to the polarization beam split plane 110e and are positioned at distances of $L1$ and $L2$ from the polarization beam split plane 110e. On a light-receiving plane of the polarization component 11e toward the N beams, there are located strip-shaped convex lenses such as 21e, 22e, which result from

09678652 "100400"

cutting a spherical flat convex lens into strip-shaped configurations, by the number of N in such a manner as to correspond to the positions of the respective N parallel beams. Here, the enlarged diagram and the cross sectional enlarged diagram of the strip-shaped convex lenses are illustrated in FIGS 49A to 49D and FIG. 42, respectively. The laser beams having passed through an array 20e of these strip-shaped convex lenses, as illustrated in FIG. 42, become converged lights each, then being launched into the polarization beam split plane in parallel to each other.

The respective converged beams are circularly polarized lights or linearly polarized lights polarized at 45 degrees toward the polarization beam split incidence plane 110e. Consequently, as illustrated in FIG. 42, an S-polarized component of an incident light 82e is reflected on this plane, and a P-polarized component thereof passes through this plane. As illustrated in FIG. 42, a reflected converged light 822 passes through the prism 111e, then being launched into the plane 1101 parallel to the polarization beam split plane 110e at an incident angle of 45 degrees. A converged beam 822' that has undergone a total reflection on the plane 1101 is S-polarized, and thus is reflected on the beam split plane 110e again. A reflected converged beam 822" passes through the prisms 111e, then going through.

Meanwhile, with respect to the P-polarized

004001 2382950

component, a converged beam 821 having passed through the beam split plane 110e passes through the prism 112e, then being launched into the plane 1102 parallel to the beam split plane 110e at an incident angle of 45 degrees. The reflected light becomes a totally reflected converged beam 821', then being launched into the beam split plane 110e again. The incident light is P-polarized, and thus passes through the beam split plane by substantially 100%. This transmittance light 821" passes through the prism 111e, then going through.

The total reflection planes 1101, 1102 of the prisms 111e, 112e are positioned at the distances of L1 and L2 from the beam split plane. The values of L1 and L2 satisfy the following relation: $\sqrt{2} (L2 - L1)$ is equal to $P/2$ that is one-half of the pitch P of the N parallel beams 8. Accordingly, when the lights having been separated by the beam split plane go through the polarization component, the two lights are shifted to each other by the amount of $P/2$. As a result, the N converged beams with the pitch of P that have been launched into the polarization component 11e pass through the polarization component 11e in a state of being formed into 2N converged beams with the pitch of $P/2$.

On a light-emitting plane of the prism 111e in the polarization component 11e, as illustrated in FIG. 43, there is located a pinhole array mask 2 where pinhole apertures 211e having a diameter d are arranged

09628692-1004-00

by the number of $2N$ with a pitch of $P/2$. The converged lights pass through the pinhole apertures. Since the portion other than the $2N$ pinhole apertures light-shields lights, the pinhole array mask 2 light-shields
5 a stray light differing from the converged lights and becoming a noise light. As a result, the lights having passed through the pinhole array mask generate spot array lights only from the pinhole portions.

The lights having passed through the pinhole
10 array 2e are linearly P-polarized lights and linearly S-polarized lights alternately every adjacent spots. Directly behind the pinhole array 2e, there is located a quarter wave plate 3e. The quarter wave plate is set in such a manner that the optical axis forms 45 degrees
15 toward the P-polarized and S-polarized directions. Consequently, the P-polarized and the S-polarized lights having passed through the quarter wave plate 3e become right-handed and left-handed circularly polarized lights, respectively.

20 The $2N$ parallel circularly polarized lights having passed through the quarter wave plate 3e are launched into a polarization component 12e. The polarization component 12e is a polarization beam splitter the structure of which is substantially the
25 same as that of the above-described polarization component 11e. Namely, a beam split plane 120e permits a P-polarized light to pass through and causes an S-polarized light to be reflected. Also, the values of

09678888-100400

L1' and L2' satisfy the following relation: $\sqrt{2} (L2' - L1') = \pm P/4$. Here, L1' denotes a distance between the beam split plane and a total reflection plane 1201 of a prism 121e through which the S-polarized light passes
5 after having been reflected by the beam split plane. L2' denotes a distance between the beam split plane and a total reflection plane 1202 of a prism 122e through which the P-polarized light passes after having been reflected by the beam split plane. By providing the
10 above-explained configuration, the 2N parallel beams with the pitch of P/2 that have been launched into the prism 12e are formed into mutually parallel 4N diverged beams with a pitch of P/4, then being emitted from the prism 12e.

15 As described above, the lights emitted from the 2N spots existing on the pinhole array mask are formed into the above-described 4N multi-spot lights by the polarization component 12e. At this time, the polarization component 12e makes the 4N multi-spot
20 lights look as if the multi-spot lights were emitted from the surface of the mask 2e. Namely, when seen from the side on which the multi-spot lights have already passed through the polarization component 12e, the 4N multi-spot lights are formed on the surface of
25 the mask 2e, then being emitted therefrom in the state of having become the diverged lights. This phenomenon is caused by a mirror image effect by the reflection planes 120e, 1201, and 1202.

05678552 100400

As one example, assuming that the number of N is equal to 16 and the pitch P is equal to 1.6 mm, in the above-described embodiment, the number of the multi-spot lights and the pitch become equal to 64 and 0.4 mm, respectively. By launching the multi-spot lights into an objective lens of an infinite focal point microscope through an image-forming lens, assuming that the magnification of the optical system is 20 times, it becomes possible to irradiate a sample, i.e., a target to be inspected, with 2 μ m-diameter spots with a 20 μ m pitch by the number of 64 simultaneously. This will be explained in detail later.

In the above-described embodiment in FIG. 41A, the N/2 multi beams are launched into the 2nd beam-doubling prism array 4e. When N is equal to 8, if the laser light-source is not the He-Ne laser type producing a large output but a large intensity is required as the irradiation light, it is sufficient to prepare, for example, 8 He-Ne lasers and to launch the lasers into the 2nd beam-doubling prism array 4e with a 1.6 mm pitch. Also, it is sufficient that 8 semiconductor lasers are used and are formed into mutually parallel beams, thereby configuring 8 beams as is the case with the above-described He-Ne lasers so as to launch the lasers into the 2nd beam-doubling prism array 4e. In this case, since the pitch P is set to be 1.6 mm, the spacing 2P between adjacent beams of the 8 laser beams becomes equal to 3 mm, which is greater

09678652 100400

5 In this way, even in the state where, by the
2nd beam-doubling prism array, the pitch is made equal
to the spacing P that is less than 4 times as great as
a diameter d of the beams emitted from the laser light-
source, i.e., $4d$ or less, causing the beams to be
10 launched into the multi-spot light forming unit using
the polarization component allows the spacing to be
made equal to $1/2$ thereof. Also, using the polariza-
tion component a plurality of n times allows the
spacing to be made equal to $1/2^n$ thereof. In this way,
15 it becomes possible to execute the conventionally
difficult following task: Converting the plurality of
 N laser beams, which are launched with the pitch that
is less than 4 times as great as the beam diameter d ,
into the $2^M N$ multi laser beams with the pitch of $P/2^M$,
20 thereby allowing the multi-spot lights to be formed
with a high-efficiency.

FIG. 44 is a diagram for illustrating another embodiment for forming the multi-spot lights according to the present invention. In the present embodiment, the N multi beams to be launched into the polarization component are formed using one laser light-source. For example, in the case where, like YAGSHG laser, the output of the light-source is large, the one laser

light-source is effective enough. In such a case, as illustrated in FIG. 44, in addition to the 2nd beam-doubling prism denoted by 4e in FIG. 41A, the 2nd beam-doubling prisms the dimensions of which are 2 times, 4 times, and 8 times the dimension of the above-described 2nd beam-doubling prism 4e are arranged in a cascaded manner at $n = 4$ stages in total.

Namely, one beam 80e emitted from one light-source is launched into the 8-times-dimensioned beam-doubling prism 441, thereby obtaining 2 beams 801 and 802 with a spacing of $8P$. The 2 beams are launched into the 4-times-dimensioned beam-doubling prisms 431 and 432, thereby obtaining 4 beams 8011, 8012, 8021, and 8022 with a pitch of $4P$. The 4 beams are launched into the 2-times-dimensioned beam-doubling prisms 421, 422, 423, and 424, thereby obtaining 8 beams with a pitch of $2P$. The 8 beams are launched into the previously-mentioned 8 beam-doubling prisms 411, 412, 413, 414, 415, 416, 417, and 418 illustrated in FIG. 41B, thereby obtaining 16 beams with a pitch of P . This allows the 16 beams with the 1.6 mm pitch to be obtained from the one beam emitted from the one laser light-source.

The method explained in the above-described embodiment makes it possible to form the multi-spot lights having a total energy that is 70% or more of the energy of the laser beam emitted from the laser light-source, which was impossible in the prior art.

09678652-100400

Moreover, taking the following measures makes it possible to form the multi-spot lights having a total energy that is 90% or more of the energy of the laser beam emitted from the laser light-source: Equip-
5 ping the optical components with an antireflection coat, providing the optical components with a multi-layer coat for lowering the loss at the time of the beam separation, performing positioning of the incident lights toward the pinhole array, or the like.

10 Furthermore, the method explained in the above-described embodiment makes it possible to restrain the variation in the respective spot energies among the multi-spot lights within $\pm 20\%$, which was impossible in the prior art.

15 Still further, taking the following measures outstandingly lowers a variation in the beam intensity caused by the reflection and the interference of the beams on the optical component surfaces, thereby making it possible to form the multi-spot lights that allow
20 the variation in the respective spot energies among the multi-spot lights to be restrained within $\pm 10\%$: Submitting conditions on the multi-layer coat at the time of the beam separation and controlling the manufacturing thereof, or bonding, with an optical
25 adhesive, the mutually adjacent components out of the optical components such as the polarizer 11e in FIG. 41A, the strip-shaped convex lens array 20e the detail of which is illustrated in FIG. 41C, the pinhole array

09678652 100400

2e, the wavelength plate 3e, and the polarizer 12e.

Incidentally, although, in the above-described embodiments, the explanation has been given concerning the case of forming the 64 or 16 multi-spot
5 lights, the present invention is not limited thereto and is effective in the case of $N = 2$, i.e., the case of obtaining 8 or more of the multi-spot lights.

Next, referring to FIG. 45, the explanation will be given below concerning an embodiment where the
10 beams obtained by the multi-spot light forming methods explained so far are applied to the fluorescent light detection, especially to the DNA inspection using the fluorescent light detection.

In FIG. 45, numerals 8001, 8002, 8003
15 denote laser light-sources, and include 8 lasers in total that are not illustrated though. The beams emitted from the respective laser light-sources are directed into one direction in parallel to each other with a pitch of about 1.6 mm by mirrors 8011, 8012,
20 8013 that are several mm in size. The 8 beams are obtained by the above-described method from the polarization component 12e as if the 64 multi-spot lights were emitted from the mask surface 3e with the 0.4 mm pitch. The 64 multi-spot lights pass through an
25 image-forming lens 61e, a mirror 63e, a wavelength selection beam splitter 70e, then being illuminated onto an inspection plane 51e of a DNA chip 5e through an objective lens 60e.

09678652 100400

There exist various types of fluorescent materials to be added to the target DNA. The fluorescent material in the present embodiment absorbs the He-Ne laser light at the wavelength of 633 nm and emits the fluorescent light at the wavelength of 670 nm. The fluorescent light is received by the objective lens 60e, and the transmittance light is reflected by the wavelength selection beam splitter 70e, thereby being guided into a detecting optical system. The wavelength selection beam splitter 70e is a multi-layer coat beam splitter for permitting the 633 nm light to pass through and causing the 670 nm light to be reflected.

The fluorescent light reflected at the beam splitter 70e is reflected at a mirror 71e, then passing through an image-forming lens 62e. The image-forming lens 62e is configured as a telecentric optical system, so that primary light-rays of the fluorescent lights,

which have been generated from the respective multi-spot lights with which the fluorescent materials on the DNA chip surface are irradiated, travel in parallel to each other after passing through the image-forming lens 5 62e. As a consequence, at an incident angle that is common to all the fluorescent lights, a fluorescent light generated from whatever multi-spot light is launched into a wavelength separating beam splitter reflecting the fluorescent lights at the above-
10 described wavelength. This condition permits the 633 nm excitation light to pass through the beam splitter in a state of being scarcely reflected. Here, the 633 nm excitation light is a noise component contained slightly in amount in the fluorescent light generated
15 from whatever multi-spot light. Namely, although the 633 nm excitation lights reach a wavelength separating beam splitter 72e slightly in amount, the excitation lights are caused to pass through the beam splitter. As a result, only the fluorescent lights are reflected,
20 then traveling toward detectors 91, 92.

The above-described excitation light, which has been reflected on the DNA chip and then travels toward the detector side, has a light intensity that is stronger by several orders or more in comparison with a
25 light intensity of the fluorescent light generated. On account of this, as described above, it is impossible to separate the excitation lights using the wavelength separating beam splitter 70e alone. In particular, the

00400T" 25932960

incident angles of the excitation lights into the beam splitter 70e differ, depending on the positions of the excitation light spots. Accordingly, it is impossible for any spot to eliminate the corresponding excitation light equally. In contrast to this, as explained above, the wavelength separating beam splitters 72e, 73e located between the telecentric image-forming lens 62e and the detectors 91, 92 are capable of reflecting the light from whatever spot position on the same incidence condition. The elimination of the excitation lights like this and interference filters 74e, 75e light-shield the excitation lights almost completely, allowing only the fluorescent lights to be taken into the detectors.

15 The detectors 91, 92, which are multi-channel photomultiplier tubes, have 32 light-receiving apertures each. Spot images of the fluorescent lights are separated into two by a right-angled mirror 76e located in front of the photomultiplier tubes 91, 92, then being image-formed at substantially the positions of the light-receiving apertures of the photomultiplier tubes. There exist pinhole arrays in front of the light-receiving apertures of the photomultiplier tubes. The pinhole arrays have apertures and a pitch that are substantially equal to the dimensions of spot images that are image-formed by the DNA chip-irradiating 2 μm -diameter and 20 μm -pitch excitation multi-spot lights with a magnification M of the objective lens and the

09678652 100400

image-forming lens. Namely, the pinhole arrays have the apertures $2M \mu m$ in diameter and the pitch of $20M \mu m$. The pitch of $20M \mu m$ is equal to a light-receiving aperture pitch of the photomultiplier tubes.

5 This corresponds to performing the simultaneous irradiation with the multi-spot light array and performing the confocal point detection toward the generated fluorescent lights, thereby making it possible to execute the fluorescent light detection
10 having a high signal-to-noise ratio. The 64 signals obtained are amplified by a circuit not illustrated, and are converted into digital information by an A/D (analogue/digital) converter, thus being transferred to a CPU (processing circuit) not illustrated. Then, data
15 on the fluorescent light intensities at the irradiation positions is stored.

 Stages 501, 502 are driven, thereby determining the fluorescent light intensities at the different positions in sequence in accordance with the above-
20 described method. In order to execute the fluorescent light detection having a high signal-to-noise ratio, the pitch of the irradiation spots is made equal to several to tens of times the diameter of the irradiation spots. Accordingly, so as to accomplish the
25 entire surface detection all over the target to be inspected, the detection is performed by driving the xy stage not only in a direction perpendicular to the arrangement of the multi-spot lights but also in the

0967853-100400

arrangement direction.

FIG. 46 is a diagram for illustrating an embodiment in the present invention. The parallel beams 8e emitted from the one laser light-source or the plurality of laser light-sources are the circularly polarized lights or the linearly polarized lights polarized at 45 degrees toward the paper surface. One beam among the plurality of parallel beams 8e is launched into the one lens 21e within the array 20e of the strip-shaped convex lenses and becomes the converged beam, then being launched into a birefringent material such as calcite. A polarized component of an ordinary ray thereof travels straight without being altered, and a polarized component of an extraordinary ray thereof is refracted. A thickness of this polarization component is set so that a spacing between the ordinary ray and the extraordinary ray at the time of having passed through the polarization component becomes equal to one-half of the arrangement pitch P of the plurality of N incident beam lights 8e. As a result, after having passed through the polarizer 11e', 2N converged beams travel with a pitch of P/2 in parallel to each other.

In the respective beams, the polarized directions in their linearly polarized states differ from each other alternately by 90 degrees. The respective beams are caused to pass through the quarter wave plate 3e having the optical axis that forms 45

004001 25982950

degrees toward the polarized directions, or a half wave
plate 3e having an optical axis that forms 22.5 degrees
toward the polarized directions, thereby obtaining
circularly polarized lights or linearly polarized
5 lights having polarized directions polarized at ± 45
degrees toward the paper surface. These 2N beams are
launched into a polarizer 12e'. The polarizer 12e' is
a calcite the thickness of which is one-half of that of
11e'. The beams have passed through the polarizer
10 12e', which obtains 4N converged beams with a pitch of
P/4.

These lights are caused to pass through a
wavelength plate 3e' that is the same as the above-
explained wavelength plate, thereby becoming circularly
15 polarized lights or linearly polarized lights polarized
at 45 degrees toward the paper surface. These multi
beams are launched into a plate 2e including a multi-
aperture array that has a pitch and an aperture
diameter. Here, the pitch is equal to the pitch of the
20 multi beams, and the aperture diameter is substantially
equal to a converged diameter determined by the lens
21e and the diameter of the beams launched into the
lens. This makes it possible to obtain noise-free
multi-spot lights including only the lights having
25 passed through the apertures.

FIG. 47 is an embodiment-illustrating diagram
for indicating a multi-spot light forming method used
for the confocal point detection in the present

004007" 25987960

5

10

15

20

25

prisms 11e, 12e, and 8 spot lights are generated in the y direction by the beam 2-splitting method using the calcite. Consequently, as illustrated in FIG. 48, 64×8 spot lights are generated in total.

5 FIG. 49 indicates a confocal point detecting method using the above-described 64×8 multi-spot lights. In FIG. 49, the same reference numeral as that in the other drawings denotes the same component. The 8 beams emitted from a laser light-source and formed by
10 an 8-beam optical system 800 are launched into the 64×8 multi-spot light-forming optical system 100e illustrated in FIG. 47. Then, in accordance with the above-described method, the 64×8 multi-spot lights illustrated in FIG. 48 are being emitted effectively from
15 the mask surface 3e.

These multi-spot lights are reduced in size and are projected onto a surface of a target 5e' to be measured, using a half mirror 70e', the image-forming lens 61e, and the objective lens 60e. The projected
20 multi-spot lights are reflected on the surface to be measured, and pass through the objective lens 60e, the image-forming lens 61e, and the half mirror 70e', then being image-formed onto a surface of a 64×8 -pinhole mask 901' located directly in front of an image-pickup
25 surface of a detector 90'. The lights having passed through the pinholes reach the image-pickup surface of the detector. If the surface of the to-be-measured target coincides with an image-forming plane of the

00400T 2292950

projected multi-spot lights, the reflected light are
image-formed on the pinholes of the pinhole mask,
thereby making it possible to obtain the strong
detected values. If the surface of the to-be-measured
5 target does not coincide with the image-forming plane,
out-of-focused spread lights reach the pinholes of the
pinhole mask 901', and accordingly the intensities of
the lights having passed through the pinholes become
lower. Consequently, by executing the above-described
10 detection with the to-be-measured target being
displaced in an up-and-down direction by z-stage 503'
shown in Fig. 49, it becomes possible to obtain the
heights at the positions of the respective spots from
their z direction values from which the detection
15 maximum intensities at the respective positions can be
obtained.

In the above-explained confocal point detect-
ing method in FIG. 49, when the target to be measured
is fixed in the x, y directions, if, for example, the
20 spot diameter is 1 μm and the spot spacing is 8 μm on
the surface to be measured, only information about the
64 \times 8 points with a 8 μm spacing can be obtained.
Accordingly, it is required to detect the confocal
point images at the other positions in sequence by
25 displacing xy stage 501', 502'. FIG. 50 is an
embodiment-illustrating diagram in the present inven-
tion, where there is indicated a method of obtaining
the 2-dimensional confocal point images. The driving

0040400 100400 259899 05678653

directions x' , y' of the xy stage in FIG. 49 and the arrangement directions of the multi-spot lights to be projected onto the to-be-measured target are shifted slightly to each other as illustrated in FIG. 50. In the case of the 64×8 multi-spot lights, an angle θ formed between these two directions is set so that $\tan \theta$ becomes equal to $1/8$. On account of this shifting, scanning the stage in the y' direction results in irradiating empty positions between a spot 011 and a spot 021 with 7 spots, i.e., 012, 013,, 018. This means that the entire surface scanning is performed all over the $1 \mu\text{m}$ spots with a $1 \mu\text{m}$ spacing placed therebetween.

The use of the above-described method irradiates the to-be-measured target with the multi-spot lights having high light intensities, and accordingly it becomes possible to detect the 64×8 spot positions in a short time. Thus, one scanning toward the samples is performed in the y' direction at a high-speed by the y stage and after the scanning, the stage is displaced slightly in the z direction, and the scanning is performed again. This operation is repeated, thereby detecting confocal point signals at the respective heights in sequence at a high-speed. In this way, a height at which the intensity is a maximum at each point is determined from the 2-dimensional intensity data at each point obtained at each height z . This makes it possible to execute the height measure-

004007 25987950

ment by the high-speed confocal point detecting method. Incidentally, setting the width of the above-described scanning to be equal to k times the pitch p of the multi-spot lights results in obtaining the 2-

5 dimensional height information where the pixel number in the x direction is equal to $64 \times 8 = 512$ and the pixel number in the y direction is equal to $8k$.

Next, the explanation will be given below concerning another embodiment for forming the multi
10 spots.

Here, taking the DNA probe array as an example, the explanation will be given concerning an apparatus and a method for measuring an intensity distribution of the fluorescent lights. The fluo-
15 rescent lights are emitted from the fluorescent markers for marking the target DNAs trapped in the state of being hybridized with the DNA probes fixed onto the large number of microscopic reaction areas on the DNA probe array. Additionally, it is needless to say that
20 the present invention is not limited to the inspection of the DNA, but is similarly applicable to the inspection and analysis of the other living body samples such as a fluorescent material-marked RNA, oligonucleotide and protein.

25 The DNA probe array to be detected is formed in the following way, for example: First, a washed glass substrate (such as a slide glass) is treated using a silane coupling agent (aminopropyltriethoxy-

004001 2592950

silane), thereby introducing an amino group onto the surface. Next, an aldehyde group-introduced oligonucleotide is dropped on microscopic areas so as to be reacted, thereby fixing the oligonucleotide on the glass substrate. A fluorescent marker-attached DNA is prepared independently as a specimen, i.e., a target to be inspected. Then, the fluorescent marker-attached DNA is spotted onto the oligonucleotide-fixed areas on the substrate so as to be trapped on the substrate by being hybridized therewith, thereby preparing the array to be measured. Incidentally, in order to fix the oligonucleotide on the glass substrate, the following methods are allowable: The surface treatment of the slide glass is performed using poly positive ions such as polylysine, thereby causing the electrostatic bond with electric charges of the DNA. Besides, the oligonucleotide is synthesized directly on the glass substrate, using a photolithography technique and a solid phase synthesizing technique. Being not limited to the above-described forming method, the DNA probe array can be formed by various well-known methods, and is measurable in much the same way.

FIG. 51 is a schematic diagram for illustrating the entire configuration of one embodiment of a fluorescent marker distribution measuring apparatus (DNA probe array measuring apparatus) according to the present invention. The apparatus includes a main body of the DNA probe array measuring apparatus, a data

09676652 100400

processing/controlling unit 19f, and a monitor 21f. A
substrate (DNA probe array) 2f is fixed on a XYZ
driving unit 20f. A light from a light-source 10f of
laser or the like is caused to pass through a multi
5 light-source distribution unit 11f, thereby being
emitted as a plurality of lights (100a, 100b, ...) that
are located on straight lines equally and uniformly.
These lights are collimated by a lens 12f, and are
reflected downward by a dichroic mirror 13f, and are
10 converged by an objective lens 14f, finally forming
excitation spots (101a, 101b, ...) onto the substrate 2f.
In the drawing, although only 2 of the lights and 2 of
the excitation spots are illustrated for concern with
the paper space, 64 excitation spots are formed
15 actually. The larger the number of the excitation
spots is made, just like 16, 32, 64, ..., the more
effective it becomes to implement the high-speed and
high-sensitivity characteristics. Namely, if the total
detecting time is the same, the larger the number of
20 the spots becomes, the more likely it is to be able to
lengthen the irradiating time per excitation spot and
to be able to enhance the sensitivity. Also, if the
irradiating time per excitation spot is the same, the
larger the number of the spots becomes, the more likely
25 it is to be able to shorten the total detecting time.
In this case, 64 times speeding-up becomes executable.

Emitted lights (fluorescent lights, scattered
light, reflected lights) generated from the excitation

09678652 "100400

spots on the substrate 2f are converged again by the objective lens 14f, and are caused to pass through the dichroic mirror 13f (a 2-color property mirror for causing wavelength components of the excitation lights to be reflected and permitting longer wavelength components of the fluorescent lights to pass through), thereby extracting the fluorescent light components. Moreover, the fluorescent light wavelength components pass through an interference filter 15f deigned to permit the fluorescent light wavelength components to pass through. In addition, the fluorescent light components are converged by a lens 16f, thereby causing images of the excitation spots (101a, 101b, ...) to be image-formed as fluorescent light images (102a, 102b, ...).

A multi-detection unit 17f substantially simultaneously detects fluorescent light intensities generated from the plurality of excitation spots. Light signals from the multi-detection unit 17f are converted into numerical values by an A/D conversion unit 18f in harmony with a timing from the data processing/controlling unit 19f, then undergoing the processing such as various arithmetic operations by the data processing/controlling unit 19f. Also, the data processing/controlling unit 19f controls displacement of the XYZ driving unit 20f, and constructs a 2-dimensional distribution of the fluorescent light intensities on the substrate 2f in combination with the

09678652 100400

5

10

In order to measure the fluorescent lights
all over the entire surface of an attention-paid area

of the substrate 2f, the XYZ driving unit 20f is displaced in the following way: FIG. 65 is an explanatory diagram for explaining an example of the displacement of the XYZ driving unit 20f. The arrangement direction of the excitation spots is taken as an x axis. As illustrated in the drawing, the excitation spots S0, S1, S2, ..., S63 are located in their initial positions in such a manner that the position of the excitation spot S0 becomes (0, 0), i.e., $(x, y) = (0, 0)$. An area 700 is the attention-paid area to be measured which includes the oligonucleotide-fixed areas on the DNA probe array. In order to scan the entire surface of the area 700, the stage is displaced in a 2-dimensional manner. In the drawing, an arrow illustrates an orbit along which the excitation spot S0 is moved relatively to the area 700.

First, all the width of the area 700 is scanned in the y direction. Then, the y positions are returned back to 0, and the spots are shifted by the amount of the excitation spot diameter (in the present example, $2 \mu\text{m}$) in the x direction. All the width of the area 700 is scanned again. This operation is repeated a plurality of times by the time the excitation spot S0 reaches the first position of S1. In the drawing, for simplicity, the scale-reduced illustration is given in such a scale that the spacing between the excitation spots is equivalent to $8 \mu\text{m}$, and there is illustrated a manner where the positions in the x

00400T 2592950

direction are changed 4 times so as to scan all the width in the y direction. Incidentally, in the case where the excitation spots are equal to $2 \mu\text{m}$ in diameter and the spacing between the excitation spots is equal to $20 \mu\text{m}$, it turns out that the above-described operation has been repeated 10 times. This makes it possible to detect the entire surface of the area the width of which is $x = 0$ to $1280 \mu\text{m}$. The next operation is as follows: The y positions are returned back to 0 and the spots are shifted by $1260 \mu\text{m}$ in the x direction, thereby displacing the spots to an area that is adjacent to the area where the scanning has been finished using the 64 excitation spots. Namely, the spot S0 is displaced to the position corresponding to S64, and the above-described operation is repeated. This is repeated, thereby scanning the entire surface of the area 700.

FIGS. 66A, 66B are diagrams for illustrating displacement curves of x, y axes of the XYZ driving unit 20f. FIG. 66A illustrates a displacement state of the XYZ driving unit in the x direction, and FIG. 66B illustrates a displacement state of the XYZ driving unit in the y direction. As is illustrated in the drawing, the operation of the present driving unit is characterized by repeating at least 2 types of displacement patterns in the x direction, i.e., the arrangement direction of the excitation spots, thereby scanning the entire surface of the to-be-measured area.

09678652-100400

Here, the 2 types of displacement patterns are step-like displacements with a microscopic width of $2\text{ }\mu\text{m}$ at n times (in the present example, 10 times) and a subsequent step-like displacement with a longer width at one time. This characteristic results from the existence of a limit to the objective lens' field-of-view size and the existence of a restriction to the spacing between the plurality of excitation spots. If the spacing between the excitation spots is made equal to a width obtained by substantially equally dividing the entire surface of the to-be-measured area by 64, it becomes unnecessary to employ the displacement method as described above. Namely, in the x direction, it is all right to repeat the step-like displacements with the microscopic width of the excitation spot diameter. In this case, however, the spacing between the excitation spots at both ends gets large, becoming substantially equal to a width of the entire surface of the to-be-measured area. This width exceeds the field-of-view width of a common objective lens (i.e., an objective lens being able to form the excitation spots of about $2\text{ }\mu\text{m}$), thereby making it difficult to execute the measurement. If there should exist an objective lens having a sufficiently large field-of-view, the numerical aperture will become smaller or such an objective lens will be an extremely expensive one, either of which is unrealistic. Namely, the scanning method illustrated in FIGS. 65, 66A, and 66B is a

09678652 100400

method suitable for scanning the entire surface of the to-be-measured area with the use of the plurality of excitation spots.

Also, as timings of the data collection at the time of the scanning, there exist 2 timings, i.e., the timing at the time of the displacement in the x direction and the timing at the time of the displacement in the y direction. In principle, either of the timings makes it possible to obtain the information on the entire surface. However, it is advantageous to collect the data in harmony with the displacement in the y direction in particular. This is due to the following reasons: A stroke of the displacement at one time is longer in the y direction, and accordingly the connection with the adjacent pixel is more clear, and thus it is easy and secure to reconstruct an image from the measured data.

Next, the explanation will be given below concerning the configuration of the multi light-source distribution unit 11f. When the size of the excitation spots is 2 μm in diameter and the spacing between the excitation spots is 20 μm , at a light-emitting end of the multi light-source distribution unit 11f, the following is required: Assuming that a coupled magnification including the objective lens is 20 times, the lights need to be emitted from 64 portions under the condition that, at the light-emitting end, the size of the light spots is 40 μm in diameter and the spacing

09673652 100400

between the excitation spots is $400\text{ }\mu\text{m}$. Since it is usually impossible to arrange the light-sources with the spacing of $400\text{ }\mu\text{m}$, the following configurations have been constructed in the present invention. These 5 configurations will be explained below, using FIGS. 52 to 57, and FIGS. 67 to 69.

FIG. 52 is a diagram for illustrating the configuration of an embodiment of a multi light-source distribution unit 11f for splitting lights emitted from 10 n laser light-sources (2 of them are illustrated in the drawing) into $4n$ lights. Lights emitted from laser light-sources (10a, 10b) are each converged by lenses (200a, 200b), thereby being introduced into optical fibers (201a, 201b). Each optical fiber has 2 branch- 15 ing portions halfway, by which each of the converged lights is split into 4 lights. Accordingly, the excitation lights can be split just like 100a1, 100a2, ... 100b4. Incidentally, as the branching portion, it is possible to select not only the 2-branching type as 20 illustrated in the drawing but also the other various types such as a 4-branching type. Also, in such a branching, there is employed a fiber that allows a light to be split equally. For example, light-emitting ends of optical fibers the core diameter of which is 25 equal to about $40\text{ }\mu\text{m}$ are arranged with the spacing of $400\text{ }\mu\text{m}$ on a straight line, then projecting the lights in a 1/20th scale-reduced state. This makes it possible to implement the configuration in the present

09678662 100400

embodiment.

FIG. 53 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit 11f for simply arranging
5 lights emitted from m laser light-sources (4 of them are illustrated in the drawing) with the spacing of 400 μm on a straight line. The case $m = 4$ is illustrated in the drawing. Lights emitted from the laser light-sources (10a, 10b, 10c, 10d) are each converged by
10 lenses (200a, 200b, 200c, 200d), thereby being introduced into optical fibers (202a, 202b, 202c, 202d). Light-emitting ends of the optical fibers are arranged with the spacing of 400 μm on a straight line. This makes it possible to implement the configuration in the
15 present embodiment concerning the lights (100a, 100b, 100c, 100d) regardless of the size of the laser light-sources with the spacing of 400 μm .

FIG. 54 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit 11f utilizing the birefringent
20 material (for example, calcite, and the other materials are also usable). As illustrated in the drawing, birefringent materials 300f, 302f such as calcite and quarter wave plates 301f, 303f are combined with each
25 other in a sequence of, from the laser light-source side, the birefringent material 300f, the quarter wave plate 301f, the quarter wave plate 302f, and the quarter wave plate 303f, thereby forming a splitting

0967662-1004100

component 310f. A laser light emitted from a laser light-source 10a is launched into the above-described component through a lens 200a. At this time, the polarization surface of the laser light has been inclined by 45 degrees, or the laser light has been converted into a circularly polarized light by being caused to pass through a quarter wave plate on the way. The laser light launched into the birefringent material 300f is double-refracted, thereby being separated into an ordinary ray and an extraordinary ray. A length of the birefringent material 300f is adjusted so that the two rays are away from each other by a distance w_1 . These lights are converted into circularly polarized lights by being caused to pass through the quarter wave plate 301f further, then being launched into the birefringent material 302f. Each of the 2 lights into which the light has been split is further split into 2 lights similarly. A length of the birefringent material 302f is adjusted so that the distance between the 2 lights becomes equal to w_2 . Making the adjustment so that w_1 becomes 2 times as long as w_2 allows the laser light to be split with an equal spacing. Incidentally, in order to let $w_2 = 400 \mu\text{m}$, it is all right to set the lengths (in the optical axis direction) of the birefringent materials 300f and 302f to be about 8 mm and about 4 mm, respectively (in the case where the birefringent materials are calcite and the crystalline axes form 45 degrees toward the optical

004001 25982950

This configuration allows the 1 laser light to be split into the 4 laser lights equally and with substantially the same intensity, and permits the light-emitting ends to be located on a straight line. Thus, locating 16 laser lights with a spacing of $0.4 \times 4 = 1.6$ mm allows 64 light spots to be located with a spacing of 0.4 mm on a straight line.. Incidentally, setting a focal point position of the lens 200a to be the position of pinholes 304f makes it possible to eliminate extra lights such as scattered lights. Accordingly, it becomes possible to make beautiful the configuration of the excitation spots on the substrate 2f, thereby permitting the resolution to be enhanced. Furthermore, the focal point position can be utilized as one focal point position for measuring the confocal point.

25 Also, although the splitting component 310f
in the drawing has the configuration of executing the
splitting with the 2 stages, it is also possible to
employ 3 stages, 4 stages, and 6 stages. In these

cases, it turns out that one laser light is split into 8, 16, and 64 lights, respectively, and the number of the laser lights required to obtain the 64 light spots can be made smaller like 8, 4, and 1. For example, in 5 the case of a 6-stage configuration where there are employed the birefringent materials the respective lengths of which are 32, 16, 8, 4, 2, and 1 mm in sequence from the light-incoming side, it is possible to split the 1 laser light into 64 lights with a 10 spacing of 0.1 mm.

FIG. 55 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit 11f. The components mainly includes 4 trapezoid-shaped glass prisms 361, 362, 363, 15 and 364 and a quarter wave plate 367. The glass prisms 361, 362, 363, and 364 are connected to each other as illustrated in the drawing, and connected planes 365, 366 are polarization beam splitters. The respective glass prisms differ slightly in their dimensions. 20 Thus, an incident light in a circularly polarized state is split into 2 lights on the connected plane 365, then becoming proximate to each other after the total reflection. At this time, making the optical path lengths differ from each other allows 2 parallel laser 25 light-fluxes to be obtained. When causing the 2 lights to be launched into the components of the glass prisms 363, 364 again through the quarter wave plate 367, each of the 2 lights is further split into 2 lights by the

004001 2332950

same principle as that described above, which allows 4
light-fluxes to be formed in total. The adjustment of
heights of the trapezoid-shaped glass prisms makes it
possible to arbitrarily set a spacing between the
5 light-fluxes, thereby making it easy to obtain the
light-fluxes with the spacing of 0.4 mm, i.e., the
light-fluxes that are exceedingly proximate to each
other. In the drawing, there is illustrated the case
where the number of emitted light-fluxes is 32 with
10 reference to 8 incident light-fluxes. Incidentally, it
is also allowable to locate a pinhole plate in
proximity to the quarter wave plate 367.

FIG. 56 is a diagram for illustrating the
configuration of another embodiment of the multi light-
15 source distribution unit 11f. By using prisms 500a,
500b, ... illustrated in the drawing which have a
polarization beam splitter and a total reflection
mirror, it becomes possible to split a beam into 2
beams. The use of the prisms by the number of 8 allows
20 lights from 8 laser light-sources to be split into 16
lights. Incidentally, it is also allowable to employ,
as a portion of the polarization beam splitter, a half
mirror-shaped beam splitter where the transmittance =
the reflectance (= an order of 50%).

25 FIG. 57 is a diagram for illustrating the
configuration of another embodiment of the multi light-
source distribution unit 11f. The prisms 500a, 500b, ...
in FIG. 56 are arranged, and further thereon, there is

used a prism 510 formed by accumulating larger-sized prisms in sequence. The half mirror-shaped beam splitters split a laser light. Repeating this at 4 stages allows 1 laser light to be split into 16 laser
5 lights.

In the multi light-source distribution units of the configurations in FIGS. 56, 57, there exists a limit to a task of making the prism sizes smaller. Although the spacing between the laser lights to be
10 split is allowable down to an order of 1 mm, it is getting gradually difficult to make the spacing even narrower. On account of this, in such a case, the combined use of the distribution units with the multi light-source distribution unit in FIG. 54 or FIG. 55
15 permits the laser lights to be split into the light-fluxes with a more microscopic spacing.

In general, like the configuration of an embodiment of the multi light-source distribution unit illustrated in FIG. 67, a plurality of multi light-
20 source distribution units 550, 551 are combined with each other. This makes it possible to construct another multi light-source distribution unit. Namely, the multi light-source distribution units in FIGS. 52 to 57 and what is more, multi light-source distribution
25 units up to in FIGS. 68, 69 explained later are combined, thereby making it possible to construct another multi light-source distribution unit. Incidentally, the number of the laser light-sources is

004040 100400 2538250

selected suitably in accordance with the number of the splitting, the optical output of the laser light-source, and the light intensities of the excitation spots needed on the surface of the substrate 2f.

5 FIG. 68 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit 11f. A laser light emitted from a laser light-source 2000 is caused to pass through a lens 2001, and is scanned by a beam scanning
10 unit 2002 such as a galvanometer mirror and a polygon mirror, then being launched into end surfaces of optical fibers 3001, 3002, ... the end surfaces of which are located at a focal point position of the lens 2001 in an arc-like configuration. The other end surfaces
15 of the optical fibers 3001, 3002, ... are located with a fixed spacing. This allows the laser lights to be split into a large number of light-fluxes, thereby making it possible to implement the configuration in the present embodiment.

20 FIG. 69 is a diagram for illustrating the configuration of another embodiment of the multi light-source distribution unit 11f. The laser light emitted from the laser light-source 2000 is scanned by a beam scanning unit 2003 such as the galvanometer mirror and
25 the polygon mirror, and is caused to pass through a lens 2004, then being launched into the end surfaces of the optical fibers 3001, 3002, ... that are arranged in a line. The respective split laser lights can be

004004 2582860

Next, referring to FIGS. 58 to 63, the explanation will be given below concerning the configurations of embodiments of the multi-detection unit 17f. Like the present example, images of the excitation spots, the size of which is 2 μm in diameter and between which the spacing is 20 μm , are image-formed with an appropriate magnification. A pitch of detectors determines the magnification. The detectors 600, 601, ..., such as photomultiplier tubes and photodiodes, are arranged in agreement with the image-formed positions (FIGS. 58, 59). Otherwise, the detection is executed using a censor 602 such as a photodiode line censor, a multi-anode type photomultiplier tube, and a CCD line censor (FIGS. 60, 61). In the case of the censor 602, a spacing between the individual detectors can be made narrower in comparison with the spacing in the methods in FIG. 58 and so on. For example, in the multi-anode type photomultiplier tube, the optical system is adjusted so that a spacing between the individual anodes is substantially equal to 1 mm and 50 times image-forming magnification is accomplished. Incidentally, through the use of pinholes 610 in FIGS. 58, 59, and 60, the multi-detection unit becomes a confocal point detecting system, thereby enhancing a position resolution and a depth resolution and improv-

concerning the data detection and an image reconstruction (i.e., an operation of the data processing unit). In order to detect the signals over the area of 12 mm square in the unit of 2 μ m, the area of 12 mm square is divided into 6000 \times 6000 areas. Let these areas be represented by a reference notation: area (i, j), where i (= 0 - 5999) denotes the positions in the x direction and j (= 0 - 5999) denotes the positions in the y direction. The detection of the fluorescent light intensities based on the scanning by the irradiation spots is executed in the same way as was explained in FIG. 65. Explaining the scanning performed by the respective irradiation spots (S0, S1, ..., S63), with respect to the scanning by the irradiation spot S0, area (0, 0) is first irradiated with the irradiation spot S0 and then, following the scanning in the y direction, the irradiation spot scans the areas from area (0, 1) to area (0, 5999). With respect to the scanning by the irradiation spot S1 as well, area (10, 0) is first irradiated with the irradiation spot S1 and then, following the scanning in the y direction, the irradiation spot scans the areas from area (10, 1) to area (10, 5999). The other irradiation spots S3 to S63 perform the scanning in much the same way. With respect to the scanning by the irradiation spot S63 as well, area (630, 0) is first irradiated with the irradiation spot S63 and then, following the scanning in the y direction, the irradiation spot scans the

09678652-100400

areas from area (630, 1) to area (630, 5999).

At that time, the signals from the optical detector corresponding to each spot are sampled every time each spot passes through the areas, then being
5 A/D-converted. The signals are expressed as $\text{sig}(k, j)$, where k corresponds to a position number (0 - 63) of the spots and j takes the values of 0 to 5999 at the positions in the y direction. Namely, the signals from the spot S1 are expressed as $\text{sig}(1, j)$, $j = 0 - 5999$.
10 These signals are stored into image storing memories corresponding to the areas of area (i, j) . Letting the image storing memories be represented by $\text{image}(i, j)$ where i ($= 0 - 5999$) and j ($= 0 - 5999$) denote the positions in the x, y directions, respectively, the
15 signals obtained by the above-described scanning at one time are stored into

```
image(k×10+X,j) = sig(k,j)(X=0, k=0-63, j=0-5999).
```

Incidentally, X denotes an X position of the spot S_0
(In this case, $X = 0$).

20 Then, as illustrated in FIG. 65, the Y position is returned back to 0, and the X position is displaced by the amount of $+2\mu\text{m}$ ($X = 1$), then executing the detection in the same way. The signals obtained are stored into

```
25 image(k×10+1,j) = sig(k,j)(k=0-63, j=0-5999).
```

Repeating this operation ten times causes areas indicated by $i = 0 - 639$, $j = 0 - 5999$ in image (i, j) to be replaced by the measured signals.

```
5 image(k*10+X,j) = sig(k,j)(X=640-649, k=0-63, j=0-5999).
```

15 (i, j) (Although this area is wider than area (i, j),
it is all right to extract a needed area alone). This
image (i, j) is then converted into a picture, which is
displayed on the monitor or the like.

In the present embodiment, there are provided
the excitation spots and the optical detecting unit
corresponding to each spot. There occurs no problem if
the intensities of all the excitation spots and a
sensitivity characteristic of the optical detecting
unit coincide with each other. If not, there appears a
stripe-shaped pattern in the obtained picture. In such
a case, there is a need of a mechanism for correcting
the sensitivity characteristic for each spot. Thus, in
FIG. 51, there is provided an intensity correction

Preparing a specimen having equal fluorescent light intensities (or locating light-sources that emit lights

15 becoming a reference value is detected (the signal
intensity values obtained by subtracting the background
value). By outputting signal values sig (k, j)
corrected as

```
sig(k, j) = (sig(k, j) - back(k))corr(k)
```

20 toward the measured signals $\text{sig}(k, j)$, it becomes possible to correct a variation in the sensitivity among the spots.

In contrast to the circumstances that the ordinary apparatus uses only 1 fluorescent-light
excitation irradiation spot, the present invention
25 allows the substrate to be simultaneously irradiated
with the plurality of (64, for example) fluorescent-
light excitation irradiation spots. This condition

When detecting the entire area in a fixed time-period, it is possible to lengthen the irradiating time per irradiation spot (64 times in the present embodiment). This enhances the fluorescent-light detecting sensitivity. Also, lengthening the irradiating time per irradiation spot also makes it possible to slow the displacement speed of the stage. This enhances the mechanical stability and durability as well. Also, equating the irradiating time per point makes it possible to shorten a time needed to measure the whole of a predetermined region on the substrate. This allows the high-speed characteristic to be implemented. In particular, when enhancing the detection resolution, namely, when making smaller the size of the irradiation spots on the substrate, if a target that has been measured conventionally with a resolution of, for example, $10\text{ }\mu\text{m}$ is measured with a resolution of 1 to $2\text{ }\mu\text{m}$, it is required to measure in sequence the irradiation spot regions that are 100 to 25 times more in number. On the other hand, just like the present invention, by simultaneously irradiating the substrate with the plurality of (64) fluorescent-light excitation irradiation spots so as to execute the fluorescent light detection, it becomes possible to accomplish the high-resolution and high-speed characteristics.

Incidentally, when performing the irradiation with the split laser lights, the intensity of the

individual split laser lights becomes weaker by the amount of being split. The use of a larger output laser apparatus, however, allows this problem to be solved easily.

5 According to the present invention, it becomes possible to measure the DNA probe array and so on with a high-resolution, at a high-speed, and with a high-sensitivity.

FIG. 70 is another embodiment-illustrating
10 diagram in the present invention. Laser light-sources 211g, 212g, 213g ... emit parallel round beams that are converted from diffused lights emitted from semiconductor lasers having a wavelength of 635 nm. The K light beams emitted from the respective laser light-
15 sources are launched into multi-beam splitters 22g with a pitch P. The multi-beam splitters 22g are arranged with a pitch P by the number of K, and split each of the incident beams into 2 beams, thereby forming 2K beams with a pitch P/2 and in parallel to each other.
20 These beams have been formed into elliptically polarized lights, linearly polarized lights, or circularly polarized lights, the elliptically polarized lights having the longer axis in the directions that forms ± 45 degrees toward y, z axes of the illustrated
25 coordinate.

The 2K beams are arranged with the pitch P/2, then being launched into a multi lens 231g. The multi lens 231g is pasted on a prism 232g. The beams that

09678622 100400

have passed through the multi lens pass through the prism 232g, then being launched into multi pinholes positioned at the boundary with a prism 233g.

At both of the bases of the prisms 232g,
5 233g, trapezoid-shaped glasses that differ from each other slightly in thickness are bonded to each other. The bonded plane is formed as a polarization beam split plane. As a consequence, the beams having passed through the prism 232g are converged into the respec-
10 tive pinholes of a pinhole array 234g having the 4K pinholes with a pitch $P/4$. The pinhole array plays a role of eliminating a stray light so as to irradiate the DNA chip with the multi spots having a less noise, the stray light existing in a portion other than the
15 pinhole unit and becoming the noise.

At the time of passing through the above-described prism 232g, the lights having passed through the polarization beam split plane become P-polarized lights (linearly polarized lights perpendicular to the
20 z axis), and the lights reflected by the beam split plane become S-polarized lights (linearly polarized lights in the z axis). On account of this, the half of the lights having passed through the multi spots are the P-polarized lights, and the remaining half are the
25 S-polarized lights.

Directly behind the pinhole array, there is located a half wave plate or a quarter wave plate. The half wave plate has an optical axis inclined at 22.5

09678657 100400

degrees toward the above-described P-polarized and the S-polarized lights. Also, the quarter wave plate has an optical axis inclined at 45 degrees toward the lights. The P-polarized and the S-polarized lights
5 that have passed through such a wavelength plate after passing through the pinholes become linearly polarized lights inclined at ± 45 degrees toward the z axis in the case of the half wave plate, and become right-handed and left-handed circularly polarized lights in the case
10 of the quarter wave plate.

The lights having passed through the above-described wave plate 235g are launched into the above-described trapezoid-pasted prism 233g (Additionally, the difference in thickness between the trapezoid-
15 shaped prisms is one-half of the thickness of the above-described trapezoid-pasted prism 232g). The pasted plane, i.e., the trapezoid-shaped base of the prism, is formed as the polarization beam split plane. As a consequence, the 4K lights having passed through
20 the pinhole array and the wavelength plate are increased by 2 times in number even further, eventually having a pitch of $P/8$ and becoming 8K in number. On account of this, the lights are emitted from the prism 233g as if 8K point light sources (secondary point
25 light sources) existed at the position of the pinhole array 234g.

The lights from the 8K secondary point light sources formed in this way pass through a lens 24g, a

09678652 100400

09678653-100400
mirror 25g, a light amount adjuster 26g, a wavelength
selection beam splitter 30g, and a high NA objective
lens 3g, then image-forming images of the 8K point
light sources onto a detection plane 51g of a DNA chip
5 5g. Incidentally, the light amount adjuster 26g is
provided in order to adjust a light amount of the
fluorescent-light detection excitation lights depending
on to what extent the fluorescent material exists on
the detection plane 51g. Namely, if the concentration
10 of the fluorescent material is high all over the entire
DNA chip or fluorescent light detection sample, a driv-
ing source 260g is driven so that a ND filter 262g of,
for example, 10% is inserted into the excitation light
optical path. However, changing the intensities of all
15 the excitation light beams in this way, in some cases,
results in narrowing the dynamic range of the detec-
tion. Consequently, in such a case, it is possible to
adjust the intensities of the individual excitation
light multi spots using a light modulator array not
20 illustrated.

Also, when it is required to execute the
detection in a dynamic range of, for example, 2^N , the
following detecting method is also possible: Setting a
ND filter 261g to be 100% (i.e., there exists no ND
25 filter) and setting the ND filter 262g to be a
transmittance of $100 \times 2^{N/2} \%$, the ND filters are
exchanged so as to execute a 2-picture detection toward
the entire picture. Then, both of the detected

5 method. The present invention using the multi spots,
however, makes it possible to execute the detection at
a speed that is more than 5 times higher as compared
with the speed in the conventional methods.

The 8K point light source images that have
10 illuminated the detection plane of the DNA chip
illuminate and excite a target DNA having the fluo-
rescent material at a tip hybridized with a probe DNA.

FIG. 71 is a diagram for indicating the relationship between the multi spots and the details of an area 50g where the target DNA exists on the glass 51g of the DNA chip 5. A numeral 505 denotes a cell. The cells are arranged in the x, y directions with a fixed pitch. In each cell, a desired DNA fragment, which is also referred to as the probe DNA, is attached to the glass for each address in the arrangement of the cells. This probe DNA is a DNA that usually includes the same nucleotide sequence in each cell, and a different DNA is usually probed in a different cell. A sample solution of the target DNA obtained by attaching the fluorescent material to ends of plural types of DNA fragments formed by collecting, refining and amplifying a target to be inspected, i.e., a specimen of a creature, is poured onto the DNA chip prepared in the

above-described manner, thereby causing the hybridization to occur. Namely, a target DNA corresponding to the nucleotide sequence of the probe DNA in each cell is coupled with the probe DNA, namely, is hybridized therewith. The DNA chip in FIG. 71 has been formed in the above-explained manner.

With reference to the cells 505, the multi spots 2001g, 2002g, 2003g,, 20Mg, i.e., the pumping lights, are arranged with a pitch that is an integer multiple of the cell pitch. In the case of FIG. 71, this integer is equal to 2. The beam diameter of the multi spots is equal to substantially Δ , and the pitch between the multi spots is equal to $N\Delta$. In the case of FIG. 71, $N = 10$ and the detection is executed by dividing one cell into 5×5 pixels. An object of such a division is as follows: When a foreign substance or the like is attached in a cell, the foreign substance generates a strong fluorescent light, thereby causing an error in the detected data. Accordingly, judging that a fluorescent light exhibiting a detection intensity larger than the strong fluorescent light detection intensity is generated by the foreign substance, an average fluorescent light intensity within the cell is determined by excluding the pixels where the foreign substance has been attached.

The DNA chip is scanned in the x direction as is indicated by A in FIG. 71, and when the multi spots scan the cells positioned at the right end, the multi

spots are displaced by the amount of one pixel Δ in the y direction, and the scanning is executed in the x direction again. This is repeated, and when the scanning of N pixels (in the drawing, 10 pixels) is over, the multi spots are displaced by the amount of $MN\Delta$ in the y direction, and the above-described operation is repeated, thereby scanning all the cells. FIG. 72 is a diagram for illustrating the above-described operation. Letting the transverse axis represent time, the longitudinal axis in an upper graph indicates the displacement quantity of the y stage, and the longitudinal axis in a lower graph indicates the displacement quantity of the x stage. On the x stage, the scanning for the detection has been executed during a time t_s , and the x stage is returned back to the initial position during a time $t_t - t_s$. The detection has been executed in the forward-step path alone. When the accuracy of the stage is sufficiently high, the detection is executable in the backward-step path as well.

As illustrated in FIG. 70, the simultaneous detection of the fluorescent lights by the amount of the M pixels is executed in the following way: The fluorescent lights generated by the irradiation with the excitation multi-spot lights are received by the objective lens 3g. Out of the transmittance fluorescent lights having passed through the objective lens, the fluorescent lights at the wavelength in proximity to 670 nm are reflected by the wavelength

selection beam splitter 30g. Then, the reflected fluorescent lights are guided into a detecting optical system. Namely, the reflected fluorescent lights pass through a mirror or a wavelength selection beam splitter, i.e., 32g, 34g, 35g, and 38g, and pass through an image-forming lens 33g, then being image-formed at light-receiving apertures of multi-channel photomultiplier tubes 101g, 102g. At the respective light-receiving apertures, there is provided a light-shielding plate where pinholes are bored, the diameter of the pinholes being substantially equal to that of the images of the excitation multi-spot lights. Only the fluorescent lights that have passed through the pinholes are detected, thereby executing the confocal point detection.

An upper graph in FIG. 73 is a graph obtained by enlarging the time axis of the lower graph in FIG. 72. In the drawing, the time t_s , which is needed to execute one scanning, is seen in more detail. In a lower graph in FIG. 73, although the transverse axis, i.e., the time axis, is identical to the transverse axis of the upper graph in FIG. 73, the longitudinal axis indicates a timing of a time of the photon counting performed by a weak light detector such as the photomultiplier tube. This graph means that the photon counting is performed during a time for which the signal level is 1 and the photon counting is not performed during a time for which the signal level is

0. During the one-sectioned time for which the signal level is 1, the signal by the amount of one pixel is detected. After the signal level becomes 0, when the signal level 1 starts next, the next pixel is detected.
- 5 Since there exist L_x pixels in one scanning in the x direction, the detecting time per pixel becomes equal to t_s/L_x or less. The time needed to perform the photon counting on the per-pixel basis is required to correspond to the position of the cell in the DNA chip.
- 10 Consequently, the signal for the starting time of the photon counting is created based on a signal from the length-measuring device for measuring the x stage's position.

- If the finishing point-in-time of the per-
- 15 pixel photon counting is determined in accordance with the information from the stage's position length-measuring device, when the stage is not displaced uniformly, the per-pixel photon counting time is varied for each pixel. This requires that the finishing time
- 20 be a time that has elapsed by a fixed time after the starting time. For the purpose of this, pulses of a high-frequency (frequency ν_r) pulse generator is counted. The counting is started from the starting of the photon counting, and the photon counting is
- 25 finished at the time when the pulse number counted reaches a fixed pulse number N_r . Namely, with reference to whatever pixel, the photon counting is executed during a time of N_r/ν_r . A control apparatus

09678652 "100400

In the above-described manner, the fluorescent lights from the 64 pixels in the x direction are detected simultaneously and, through the scanning by the stage, in sequence. Photon counting signals S_{PM} to be obtained from each pixel are detected in the manner as is illustrated in FIG. 74. Namely, focusing an attention on one photomultiplier tube out of the multi-channel photomultiplier tubes, in the case of weak detected fluorescent lights, photomul signals are obtained as photon detection pulse signals the pulse time-width of which is equal to about 30 ns with a low frequency as are illustrated in an upper graph in FIG. 74. Then, pulse signals with a fixed width are generated from the rising edges of the photomul signals. Otherwise, in the case where the photomul signals exceed a fixed signal level I_T as are illustrated in the upper graph in FIG. 74, the photomul signals are converted by a comparator circuit into fixed level signals just like the signals S_{PC} illustrated in a lower graph in FIG. 74. The pulse-shaped signals formed in this manner are counted using a

counter. This allows the detected photon number to be determined within the detecting time $t_s/L_x - \Delta t = Nr/\nu r$.

FIGS. 75A to 75D illustrate the case where the detected fluorescent light intensities are high.

5 The drawings illustrate the photomul detection signals S_{PM} and the signals S_{PC} after being comparated. The photon pulses are detected with a high frequency and accordingly, in some places, 2 or more of the pulses have been detected in a state of being superimposed on

10 each other. On account of this, among the signals after being comparated, there appear signals having larger width. S_{PC}' is a diagram resulting from enlarging a time of the signals S_{PC} between a point-in-time A and a point-in-time B. If the detection signals have been

15 detected in the state of being superimposed between a signal and a signal subsequent thereto, the pulse-widths of the signals after being comparated are increased. As a result, calculating simply the pulse number of the signals after being comparated results in

20 an increase in the error. Accordingly, as illustrated in a graph in FIG. 75D, constant high-frequency pulse signals are counted with S_{PC}' employed as the gate. The use of the counted signals S_{PWC} thus obtained makes it possible to determine the photon number more precisely

25 than counting the pulses of the S_{PC} signals. Moreover, by correcting the counted value of the S_{PWC} signals with a downward-convex univalent function $F(S_{PWC})$, it becomes possible to execute even more precise photon counting.

The above-described method, however, is insufficient to implement the even broader dynamic range requested in the DNA inspection. Namely, in the DNA inspection, the dynamic range of several photon pulses to one hundred and tens of thousands of photon pulses is requested within the time needed to detect one pixel. Nevertheless, since the width of the photon detection pulses is equal to tens of ns, when trying to implement the entire dynamic range by the photon counting, tens of ns \times one hundred and tens of thousands = several m sec become required as the per-pixel detecting time.

Accordingly, even if the number of the multi-spot excitation lights is equal to 64, when the number of the pixels is 6000×6000 , it turns out that it takes 30 minutes or so to execute the detection.

FIG. 76 illustrates an embodiment for solving this problem. The output signal of the multi-channel photomultiplier tube 101g is inputted into an analogue switch 1A. A PC 10g connects an initial condition of the analogue switch with B, i.e., a photon counting circuit 1B. This means that, when executing the fluorescent light detection on the per-pixel basis, the photon counting is executed first. FIGS. 77A, 77B, which illustrate the time-elapsing change of the photon counting signals, correspond to the case where the fluorescent lights are exceedingly weak and the fluorescent light intensities are detected by the photon

09078652-100400

counting detection.

FIG. 77A illustrates the pulse signals S_{pc} formed by binarizing the photon pulse signals with the use of the comparator, the photon pulse signals having been detected by the photomultiplier tubes. FIG. 77B illustrates a counted signal NS_{pc} obtained by counting the pulse number of the pulse signals in FIG. 77A. If the count signal NS_{pc} does not exceed a determined threshold value N_0 at a point-in-time at which a time α (t_s/L_x) has elapsed after the starting of the counting, the analogue switch continues the photon counting in the present state that will remain unchanged, then executing the photon counting during the per-pixel fluorescent light detecting time $t_s/L_x - \Delta t$. With respect to α in the time $\alpha(t_s/L_x)$ at which this judgement should be made after the starting of the counting, it is all right to assume α to be substantially 0.01 to 0.3. Namely, this time is satisfying enough if it is of an order of a time during which the photon counting pulses are at the maximum and approximately 10 or more pulses are detected. The above-described phrase "at the maximum" means the case where the pulse signals have been generated at the highest ultra-density within this time.

FIGS. 77C to 77E illustrate the case where the fluorescent light intensities become higher and executing the photon counting causes inconveniences to occur, namely, the case where 2 or more of the photon

09078652 100400

counting pulses are superimposed on each other at the same time or partly. In this case, the after-comparator pulse signals S_{pc} , when formed by comparing the partly superimposed pulses, are increased in their widths as illustrated in FIG. 77C. FIG. 77D illustrates a counted signal NS_{pc} of the pulse signals in FIG. 77C. The counted signal NS_{pc} exceeds the threshold value N_0 at the point-in-time $\alpha(t_s/L_x)$, which shows that the fluorescent light detection by the photon counting is not suitable for the fluorescent light intensities at the point-in-time. Thus, at this point-in-time, the analogue switch in FIG. 76C is connected to C so as to integrate the photomul signals in an analogue manner by an integrating circuit 1C. In this way, by judging, on the per-pixel basis, whether the fluorescent light detection should be executed by the photon counting or the analogue integration, the detection is executed in such a manner that the optimum method is selected for each detection.

Incidentally, although not illustrated, if the fluorescent light intensities become higher than those in the state in FIG. 77C, the pulses in FIG. 77C are connected with each other and as a result, the pulse-counted value become equal to several or 0. At this time, as illustrated in FIG. 75D, employing the signals S_{pwc} for counting the signals S_{pc} with the use of the rectangle-shaped high-frequency pulses with the constant frequency, a pulse-counted signal NS_{pwc} thereof

09678552 100400

is given as is illustrated in FIG. 77E. The use of the signal NS_{PWC} makes it possible to judge that the value of the signal exceeds a threshold value N_1 . Then, switching the analogue switch to C allows the analogue
5 detection to be executed without a mistake even in the case of the detection of the even higher fluorescent light intensities.

Once the switching to the analogue detection has been performed, the circuit 1C starts the analogue
10 integration with the switching point-in-time employed as the starting point-in-time. As illustrated in FIG. 78A, setting a target pixel detection starting point-in-time to be the starting point-in-time (this point-in-time is assumed to be 0), the circuit 1C starts the
15 integration from the point-in-time $\alpha(t_s/L_x)$. Then, as is the case with the photon counting, the circuit 1C continues the integration until the point-in-time $t_s/L_x - \Delta t$, and A/D-converts the integrated value at this point-in-time. The A/D-converted digital information
20 IC01 is transferred to a circuit 100g. In the case where the fluorescent light intensities are weak, the photon counting is continued, and the photon counting signals ranging from the point-in-time 0 to the point-in-time $t_s/L_x - \Delta t$ are counted. The counted digital
25 information IB01 is also transferred to the circuit 100g. The results of the photon counting digital information and the analogue integration digital information, which have been transferred to the circuit 100g

09678852 100400

in the parallel manner as described above from the respective channels of the multi-channel photo-multiplier tube 101g, are transferred to the PC 11g, i.e., the personal computer. As having been described previously, it was recognized at the point-in-time α (t_s/L_x) whether the detection executed in each channel has been executed by the photon counting or the analogue integration. Consequently, the PC 11g selects and employs the method suitable for the detection for each channel. Namely, the selection signals therefor are simultaneously transferred to the information IC01, IC02, ... in Fig. 76.

Incidentally, in the above-described embodiment, it was judged at the point-in-time $\alpha(t_s/L_x)$ which method should be selected of the photon counting and the analogue integration. However, it is also allowable to execute the detection from the beginning by both of the methods simultaneously and to perform the selection after the time $t_s/L_x - \Delta t$ has elapsed.

FIG. 78A indicates a variation in the integration signal when the analogue integration detection is executed. Between the point-in-time $\alpha(t_s/L_x)$ at which the analogue integration detection was started and the point-in-time $t_s/L_x - \Delta t$, the integrated value has been increasing with an inclination proportional to the magnitudes of the detected fluorescent light intensities. Then, the integrated value at the point-in-time $t_s/L_x - \Delta t$ undergoes the sample holding,

09678652 100400

then being A/D-converted. The analogue detection as described above makes it possible to capture the variation in the signal intensities over a dynamic range of approximately 2 order.

5 Next, referring to FIG. 78B, the explanation will be given below concerning a method of making the detection executable in the range of the detection of the even higher fluorescent light intensities. In this case, since the integrated value had been saturated
10 before the analogue integration detection reached the point-in-time $t_s/L_x - \Delta t$, the detection at this point-in-time is impossible: However, using the high-frequency pulse signals S_{hc} used in FIG. 75D, by counting $(t_F - \alpha(t_s/L_x))$, i.e., a time ranging from the
15 point-in-time $\alpha(t_s/L_x)$ at which the integration was started to a point-in-time t_F at which the integration was saturated, the detected intensity I is determined by the following equation since the integration-saturated value I_F had been known in advance:

20
$$I = I_F \cdot ((1-\alpha)t_s/L_x - \Delta t) / (t_F - \alpha(t_s/L_x))$$

In this way, measuring the time from the integration-starting point-in-time to the integration-saturated point-in-time allows the dynamic range to be enlarged by approximately 1 order further.

25 In order to count the saturated point-in-time as described above, it is well enough to add the

00400F 2392960

following function to the analogue integrating circuit illustrated in FIG. 76. Namely, setting the integration signal of the integrating circuit 1C to be the 1st input and setting a signal level equivalent to the
5 predetermined integration-saturated value to be the 2nd input, these two inputs are inputted into the comparator circuit. Then, from variations in the outputted signals resulting from the inputs, it can be assumed that the counting has been finished. This
10 allows the saturated point-in-time to be counted.

As having been explained so far, the fluorescent lights detected by the multi-channel photomultiplier tubes 101g, 102g are detected in the 64 channels in parallel, and are inputted into the circuit
15 100g in parallel and are converted into the time-sequential signals, then being transferred to the PC 11g. By scanning the x stage in FIG. 70, as illustrated in FIG. 71, the 64 pixels arranged in the y direction are detected simultaneously and, in the x
20 direction, in sequence. Although not illustrated, the optical length-measuring device is attached to each of the xy stage 4g in FIG. 70, and the length-measuring device measures the displacement quantities of the xy stage. The dimensions Δx , Δy of the fluorescent light
25 detected pixels on the DNA chip are each assumed to be, for example, 2 μm . The measurement of each pixel is started from a point-in-time at which the length-measuring device of the x stage measures the displace-

ment of 2 μm .

Hereinafter, the explanation will be given concerning a concrete embodiment of the multi-spot fluorescent light detection or the multi-spot DNA inspection according to the present invention. The scanning operation is performed in the x direction, and the shifting operation by the amount of 1 pixel on the basis of one scanning in the x direction is performed in the y direction, and the x positions are shifted by a large amount every 10 scanings. This is repeated, thereby executing the detection or the inspection in the 2-dimensional manner.

When a stage's position length-measuring signal of the measurement starting is detected by the scanning in the x direction, the photon counting is started first. It is assumed that L_x , i.e., the detected pixel number in the x direction, is equal to 6400, and the pixel pitch is equal to 2 μm , and t_s , i.e., the time needed to scan this 2 μm , is equal to 60 μsec . The width of the pulses generated after the photomultiplier tube has received 1 photon is equal to substantially 30 n sec. Consequently, when executing the photon counting during 40 μsec out of the time of 60 μsec during which the spot has passed through one pixel, it becomes possible to count hundreds to thousands of photons using the photon counting method. Toward the lights the intensities of which are higher than this, the pulse signals are connected with each

5

10

20

Although, in the above-described embodiment in FIG. 76, the detection is executed by time-dividing

5 The above-described switching between the
detecting methods is not limited to the fluorescent
light detection, but is generally effective in the case
where the per-pixel detecting time T_p is restricted to
a short time. Namely, when N_r , i.e., the ratio between
10 T_p and the time-width Δt of the photon detection
pulses, is smaller as compared with the requested
detection dynamic range N_d , namely, when

holds, the detection becomes executable in the broad
15 range extending from the weak photon counting area up
to the strong lights the photon counting of which is
impossible.

The scanning by the amount of 6000 pixels is performed in the x direction at a speed of 60 μ sec/1 pixel and at this time, in the y direction, 64 pixels are detected simultaneously with 10 pixels skipped. Accordingly, at a point-in-time at which the one scanning is over in spending 360 msec, 384000 pixels have been detected in the above-described broad dynamic range. When the one scanning is over, the stage is displaced in the y direction by the amount of 1 pixel,

i.e., $2\ \mu\text{m}$, then detecting the adjacent pixel line similarly. This operation is repeated 10 times, thereby executing the detection of 640×6000 pixels. Even if accelerating and decelerating times needed to return
5 the stage are added, the detection of the pixels in the above-described number is finished in spending 4 to 5 seconds.

Next, the stage is displaced largely in the y direction by the amount of 640 pixels, i.e., $2\ \mu\text{m} \times$
10 $640 = 1.28\ \text{mm}$, then repeating the above-described operation. Repeating this large displacement 10 times allows 6400×6000 pixels to be detected in spending substantially 40 to 50 seconds. Namely, it becomes possible to accomplish the fluorescent light detection
15 or the weak light detection of the images of 6000×6000 pixels the minimum detection intensity of which is of several photons with a resolution of $2\ \mu\text{m}$, in the dynamic range of 2^{16} , and within 1 minute.

The above-described embodiment is of the case
20 where the detecting time requested for each pixel is short. However, in the case where the per-pixel detecting time is larger by 1 order or more and the dynamic range of 2^{16} is required similarly, the method illustrated in FIG. 78B where the integration-saturated
25 time is determined becomes unnecessary. Also, if the width of the photon detection pulses from the photomultiplier tube can be shortened even further, the photon counting alone or the combination of the photon

09678652-100400

counting and the analogue integration detection makes the detection possible.

When trying to apply the DNA inspection, in particular, the DNA inspection using the DNA chip, to a usage such as group checkup where a large number of samples are dealt with, it becomes important to implement an inspecting apparatus having the characteristics of a high-sensitivity, a high-resolution, a broad dynamic range, and a high-speed. This implementation has been made possible by the following method: Using the multi-spot excitation lights or the sheet-shaped excitation beams explained in the previously-mentioned embodiments, the fluorescent lights from a plurality of pixels are detected simultaneously, and the relative positions between the excitation lights and a sample are changed by the scanning so as to detect the fluorescent lights in sequence.

Detecting the 64 ($M = 64$) pixels simultaneously has allowed the 6000×6000 pixels to be detected in spending a time less than ($300 \mu\text{sec}/\text{pixel}$), namely, the average pixel detecting time has become shorter than ($300 \mu\text{sec}/M$). As a result, it has become possible to execute the detection in a time less than 3 minutes per sample. This result can respond to and satisfy the needs of the high-speed inspection because, conventionally, it took 10 minutes or more to detect the fluorescent light images of the pixels in the above-described number. Furthermore, by using the photon

thereby making it possible to inspect the DNA. The use of the method as described above enhances the resolutions of the detected images. Utilizing the enhanced resolutions makes it possible to detect a to-be-
5 inspected DNA in a cell as the fluorescent light images and to execute the DNA inspection of the cell in the following way: For example, employing, as a sample, a desired target DNA to which a fluorescent light material has been added, the fluorescent light
10 material-added target DNA is hybridized with the corresponding DNA among 1-chain DNAs in the cell.

FIG. 79 is an embodiment-illustrating diagram of the fluorescent light detection in the present invention and, in particular, of the fluorescent light
15 detection that is effective in the DNA inspection. The same reference numeral as that in FIG. 71 denotes the same component. Instead of the multi-spot excitation lights illustrated in FIG. 71 the irradiation of which is performed with the spacing of 10 pixels, sheet-
20 shaped excitation lights 2000 are employed. As is the case with the optical system in FIG. 70, fluorescent lights obtained by the irradiation with the excitation lights are separated from the excitation lights, then being detected by the 1-dimensional photomultiplier
25 tube array or the 1-dimensional ultra-high sensitivity censor. The excitations by the sheet-shaped excitation beams are executed simultaneously over mutually adjacent, for example, 50 pixels in a 1-dimensional

09678652 "100400

light detection. In a laser 27g, there are provided windows at Brewster angle at both ends of a laser tube 271 filled with a laser medium. Laser lights emitted out therefrom are returned back by 100% reflection mirrors 272, 273. The energy of the laser light that is reciprocating between the resonator mirrors is usually more than 10 times as high as the beam energy extracted out of the laser resonator through the emitting window from the optical energy within the resonator. In the case of inserting a multi-spot or sheet-shaped beam generating hologram plate 270 into the laser resonator, since a hologram 2701 has been formed in advance so that the multi spots or the sheet-shaped beams are generated, as illustrated in the drawing, multi spots 2702 are reproduced through a lens 274. Incidentally, the laser light with which the hologram has been irradiated forms the multi-spot images at a diffraction efficiency of substantially 10%. The remaining light passes through the hologram without being varied as a 0th light, then reciprocating within the laser resonator. These multi spots are completely identical to the multi-spot lights at the time of immediately after having passed through the mask-like circular aperture array explained in FIG. 70. This condition makes it possible to irradiate a detection target with the multi spots with the use of the lens 24g in accordance with the configuration in FIG. 70. As a result, it is possible to obtain the multi-

004007 25987950

spot lights or the sheet-shaped beams the intensities of which are almost 10 times higher as compared with those in the conventional case where the hologram is located in a laser-emitting optical path. Consequently, it becomes possible to execute the high-speed and high-sensitivity fluorescent light detection and DNA inspection.

In the above-described embodiment, the explanation has been given concerning the case of the excitation lights having 1 wavelength. The present invention, however, also exhibits the effects in the case of using the excitation lights having 2 wavelengths or 3 or more wavelengths. In this case, conventionally, when trying to execute the detection using the plurality of wavelengths, it has taken an exceedingly long time to do so. On the other hand, the execution of the photon counting detection using the multi-spot lights according to the present invention makes it possible to execute the detection with a high-sensitivity and at a high-speed.

09678652-100400